


Assembler Language "Boot Camp" Part 3 - Assembly and Execution; Branching

SHARE 115 in Boston
August 3, 2009



1

Introduction

- Who are we?
 - John Ehrman, IBM Software Group
 - Dan Greiner, IBM Systems & Technology Group

2

Introduction

- Who are you?
 - An applications programmer who needs to write something in mainframe assembler?
 - An applications programmer who wants to understand z/Architecture so as to better understand how HLL programs work?
 - A manager who needs to have a general understanding of assembler?
- Our goal is to provide for professionals an introduction to the z/Architecture assembler language

3

Introduction

- These sessions are based on notes from a course in assembler language at Northern Illinois University
- The notes are in turn based on the textbook, Assembler Language with ASSIST and ASSIST/I by Ross A Overbeek and W E Singletery, Fourth Edition, published by Macmillan

4

Introduction

- The original ASSIST (Assembler System for Student Instruction and Systems Teaching) was written by John Mashey at Penn State University
- ASSIST/I, the PC version of ASSIST, was written by Bob Baker, Terry Disz and John McCharen at Northern Illinois University

5

Introduction

- Both ASSIST and ASSIST/I are in the public domain, and are compatible with the System/370 architecture of about 1975 (fine for beginners)
- Everything we discuss here works the same in z/Architecture
- Both ASSIST and ASSIST/I are available at <http://www.kcats.org/assist>

6

Introduction

- ASSIST-V is also available now, at <http://www.kcats.org/assist-v>
- Other materials described in these sessions can be found at the same site, at <http://www.kcats.org/share>
- Please keep in mind that ASSIST, ASSIST/I, and ASSIST-V are not supported by Penn State, NIU, NESI, or any of us

7

Introduction

- Other references used in the course at NIU:
 - Principles of Operation (PoO)
 - System/370 Reference Summary
 - High Level Assembler Language Reference
- Access to PoO and HLASM Ref is normally online at the IBM publications web site
- Students use the S/370 "green card" booklet all the time, including during examinations (SA22-7209)

8

Our Agenda for the Week

- Assembler Boot Camp (ABC) Part 1: Numbers and Basic Arithmetic (Self Study)
- ABC Part 2: Instructions and Addressing (Monday - 11:00 a.m.)
- ABC Part 3: Assembly and Execution; Branching (Tuesday - 9:30 a.m.)
- ABC Lab 1: Hands-On Assembler Lab Using ASSIST/I (Tuesday - 6:00 p.m.)

9

Our Agenda for the Week

- ABC Part 4: Program Structures; Arithmetic (Wednesday - 9:30 a.m.)
- ABC Lab 2: Hands-On Assembler Lab Using ASSIST/I (Wednesday - 6:00 p.m.)
- ABC Part 5: Decimal and Logical Instructions (Thursday - 9:30 a.m.)

10

Today's Agenda

- Assembly of a Complete Program
- Execution of a Complete Program
- Implicit Addresses and USING
- The Condition Code and Branching
- X-Instructions and ASSIST

11



Assembly of a Complete Program

In Which We Take Baby Steps and are Amazed at How a Program Works!



12

A Complete Program

- Yesterday, we introduced a few instructions and used them to create a complete, if short, program
- Today, we will analyze the object code generated by the assembly of the program, then look at what happens when ASSIST/I executes the program
- "Object code - nothing else matters"

13

First Demo Program, Source List

- * This program adds two numbers that are taken
- * from the 5th and 6th words of the program.
- * The sum is stored in the 7th word.

```
ADD2      CSECT
          L      1,16(,15)   Load 1st no. into R1
          L      2,20(,15)   Load 2nd no. into R2
          AR      1,2         Get sum in R1
          ST      1,24(,15)   Store sum
          BCR     B'1111',14  Return to caller
          DC      F'4'        Fullword initially 4
          DC      F'6'        Fullword initially 6
          DS      F           Rsrvd only, no init
          END      ADD2
```

14

First Demo Program, Assembled

| LOC | OBJECT CODE | SOURCE STATEMENT |
|--------|-------------|------------------|
| 000000 | | ADD2 CSECT |
| 000000 | 5810 F010 | L 1,16(,15) |
| 000004 | 5820 F014 | L 2,20(,15) |
| 000008 | 1A12 | AR 1,2 |
| 00000A | 5010 F018 | ST 1,24(,15) |
| 00000E | 07FE | BCR B'1111',14 |
| 000010 | 00000004 | DC F'4' |
| 000014 | 00000006 | DC F'6' |
| 000018 | | DS F |
| | | END ADD2 |

15

First Demo Program, Assembled

| LOC | OBJECT CODE | SOURCE STATEMENT |
|--------|-------------|------------------|
| 000000 | | ADD2 CSECT |
| 000000 | 5810 F010 | L 1,16(,15) |
| 000004 | 5820 F014 | L 2,20(,15) |
| 000008 | 1A12 | AR 1,2 |
| 00000A | 5010 F018 | ST 1,24(,15) |
| 00000E | 07FE | BCR B'1111',14 |
| 000010 | 00000004 | DC F'4' |
| 000014 | 00000006 | DC F'6' |
| 000018 | | DS F |
| | | END ADD2 |

16

First Demo Program, Assembled

| LOC | OBJECT CODE | SOURCE | STATEMENT |
|--------|-------------|--------|----------------|
| 000000 | | ADD2 | CSECT |
| 000000 | 5810 F010 | | L 1,16(,15) |
| 000004 | 5820 F014 | | L 2,20(,15) |
| 000008 | 1A12 | | AR 1,2 |
| 00000A | 5010 F018 | | ST 1,24(,15) |
| 00000E | 07FE | | BCR B'1111',14 |
| 000010 | 00000004 | | DC F'4' |
| 000014 | 00000006 | | DC F'6' |
| 000018 | | | DS F |
| | | | END ADD2 |

17

First Demo Program, Assembled

| LOC | OBJECT CODE | SOURCE | STATEMENT |
|--------|-------------|--------|----------------|
| 000000 | | ADD2 | CSECT |
| 000000 | 5810 F010 | | L 1,16(,15) |
| 000004 | 5820 F014 | | L 2,20(,15) |
| 000008 | 1A12 | | AR 1,2 |
| 00000A | 5010 F018 | | ST 1,24(,15) |
| 00000E | 07FE | | BCR B'1111',14 |
| 000010 | 00000004 | | DC F'4' |
| 000014 | 00000006 | | DC F'6' |
| 000018 | | | DS F |
| | | | END ADD2 |

18

First Demo Program, Assembled

| LOC | OBJECT CODE | SOURCE | STATEMENT |
|--------|-------------|--------|----------------|
| 000000 | | ADD2 | CSECT |
| 000000 | 5810 F010 | | L 1,16(,15) |
| 000004 | 5820 F014 | | L 2,20(,15) |
| 000008 | 1A12 | | AR 1,2 |
| 00000A | 5010 F018 | | ST 1,24(,15) |
| 00000E | 07FE | | BCR B'1111',14 |
| 000010 | 00000004 | | DC F'4' |
| 000014 | 00000006 | | DC F'6' |
| 000018 | | | DS F |
| | | | END ADD2 |

19

First Demo Program, Assembled

| LOC | OBJECT CODE | SOURCE | STATEMENT |
|--------|-------------|--------|----------------|
| 000000 | | ADD2 | CSECT |
| 000000 | 5810 F010 | | L 1,16(,15) |
| 000004 | 5820 F014 | | L 2,20(,15) |
| 000008 | 1A12 | | AR 1,2 |
| 00000A | 5010 F018 | | ST 1,24(,15) |
| 00000E | 07FE | | BCR B'1111',14 |
| 000010 | 00000004 | | DC F'4' |
| 000014 | 00000006 | | DC F'6' |
| 000018 | | | DS F |
| | | | END ADD2 |

20

First Demo Program, Assembled

| LOC | OBJECT CODE | SOURCE | STATEMENT |
|--------|-------------|--------|------------|
| 000000 | | ADD2 | CSECT |
| 000000 | 5810 F010 | L | 1,16(,15) |
| 000004 | 5820 F014 | L | 2,20(,15) |
| 000008 | 1A12 | AR | 1,2 |
| 00000A | 5010 F018 | ST | 1,24(,15) |
| 00000E | 07FE | BCR | B'1111',14 |
| 000010 | 00000004 | DC | F'4' |
| 000014 | 00000006 | DC | F'6' |
| 000018 | | DS | F |
| | | END | ADD2 |

21

First Demo Program, Assembled

| LOC | OBJECT CODE | SOURCE | STATEMENT |
|--------|-------------|--------|------------|
| 000000 | | ADD2 | CSECT |
| 000000 | 5810 F010 | L | 1,16(,15) |
| 000004 | 5820 F014 | L | 2,20(,15) |
| 000008 | 1A12 | AR | 1,2 |
| 00000A | 5010 F018 | ST | 1,24(,15) |
| 00000E | 07FE | BCR | B'1111',14 |
| 000010 | 00000004 | DC | F'4' |
| 000014 | 00000006 | DC | F'6' |
| 000018 | | DS | F |
| | | END | ADD2 |

22

First Demo Program, Assembled

| LOC | OBJECT CODE | SOURCE | STATEMENT |
|--------|-------------|--------|------------|
| 000000 | | ADD2 | CSECT |
| 000000 | 5810 F010 | L | 1,16(,15) |
| 000004 | 5820 F014 | L | 2,20(,15) |
| 000008 | 1A12 | AR | 1,2 |
| 00000A | 5010 F018 | ST | 1,24(,15) |
| 00000E | 07FE | BCR | B'1111',14 |
| 000010 | 00000004 | DC | F'4' |
| 000014 | 00000006 | DC | F'6' |
| 000018 | | DS | F |
| | | END | ADD2 |

23

First Demo Program, Assembled

| LOC | OBJECT CODE | SOURCE | STATEMENT |
|--------|-------------|--------|------------|
| 000000 | | ADD2 | CSECT |
| 000000 | 5810 F010 | L | 1,16(,15) |
| 000004 | 5820 F014 | L | 2,20(,15) |
| 000008 | 1A12 | AR | 1,2 |
| 00000A | 5010 F018 | ST | 1,24(,15) |
| 00000E | 07FE | BCR | B'1111',14 |
| 000010 | 00000004 | DC | F'4' |
| 000014 | 00000006 | DC | F'6' |
| 000018 | | DS | F |
| | | END | ADD2 |

24

First Demo Program, Assembled

| LOC | OBJECT CODE | SOURCE STATEMENT |
|--------|-------------|------------------|
| 000000 | | ADD2 CSECT |
| 000000 | 5810 F010 | L 1,16(,15) |
| 000004 | 5820 F014 | L 2,20(,15) |
| 000008 | 1A12 | AR 1,2 |
| 00000A | 5010 F018 | ST 1,24(,15) |
| 00000E | 07FE | BCR B'1111',14 |
| 000010 | 00000004 | DC F'4' |
| 000014 | 00000006 | DC F'6' |
| 000018 | | DS F |
| | | END ADD2 |

25

First Demo Program, Assembled

| LOC | OBJECT CODE | SOURCE STATEMENT |
|--------|-------------|------------------|
| 000000 | | ADD2 CSECT |
| 000000 | 5810 F010 | L 1,16(,15) |
| 000004 | 5820 F014 | L 2,20(,15) |
| 000008 | 1A12 | AR 1,2 |
| 00000A | 5010 F018 | ST 1,24(,15) |
| 00000E | 07FE | BCR B'1111',14 |
| 000010 | 00000004 | DC F'4' |
| 000014 | 00000006 | DC F'6' |
| 000018 | | DS F |
| | | END ADD2 |

26

First Demo Program, Assembled

| LOC | OBJECT CODE | SOURCE STATEMENT |
|--------|-------------|------------------|
| 000000 | | ADD2 CSECT |
| 000000 | 5810 F010 | L 1,16(,15) |
| 000004 | 5820 F014 | L 2,20(,15) |
| 000008 | 1A12 | AR 1,2 |
| 00000A | 5010 F018 | ST 1,24(,15) |
| 00000E | 07FE | BCR B'1111',14 |
| 000010 | 00000004 | DC F'4' |
| 000014 | 00000006 | DC F'6' |
| 000018 | | DS F |
| | | END ADD2 |

27

Execution of a Complete Program

In Which We See
the World Go By
in Single Steps



28

Implicit Addresses and USING

In Which We Make
Assembler Programming
"Easy"



45

A Slight Change

- What if we want to make a change to our original program? Maybe use register 12 instead of R15 for the base register
- That's no problem - just insert one LR instruction in front of the first LOAD, copying R15 to R12
- Then change all instructions which use R15 as the base register to use R12!

46

A Slight Change

- But that moves everything down and our data areas are no longer where they were, and that means we have to re-calculate the displacements

47

Updated ADD2 Demo Program

- * This program adds two numbers that are taken
- * from the 6th and 7th words of the program.
- * The sum is stored in the 8th word.
- * (How do we know which words?)

```
ADD2      CSECT
          LR      12,15      Copy addr of 1st inst
          L       1,??(,12)  Load 1st no. into R1
          L       2,??(,12)  Load 2nd no. into R2
          AR      1,2        Get sum in R1
          ST      1,??(,12)  Store sum
          BCR     B'1111',14  Return to caller
          DC      F'4'      Fullword initially 4
          DC      F'6'      Fullword initially 6
          DS      F        Rsrvd only, no init
          END      ADD2
```

48

Updated ADD2 Demo Program

- * This program adds two numbers that are taken
- * from the 6th and 7th words of the program.
- * The sum is stored in the 8th word.

```

ADD2   CSECT
      LR      12,15      Copy addr of 1st inst
      L       1,20(,12)  Load 1st no. into R1
      L       2,24(,12)  Load 2nd no. into R2
      AR      1,2        Get sum in R1
      ST      1,28(,12)  Store sum
      BCR     B'1111',14 Return to caller
      DC      F'4'       Fullword initially 4
      DC      F'6'       Fullword initially 6
      DS      F          Rsrvd only, no init
      END     ADD2
    
```

49

Updated ADD2 Demo Program

- As you are looking at the previous and next slides, you should ask yourself
 - why did displacements increase by 4 and not 2?
 - why did the locations of the three data areas increase by four bytes, when we added only a two-byte instruction at the beginning of the program?
- Specifically, notice that BCR occupies only two bytes of storage

50

Updated ADD2 Demo Program Assembled

| LOC | OBJECT CODE | SOURCE STATEMENT |
|--------|-------------|------------------|
| 000000 | | ADD2 CSECT |
| 000000 | 18CF | LR 12,15 |
| 000002 | 5810 C014 | L 1,20(,12) |
| 000006 | 5820 C018 | L 2,24(,12) |
| 00000A | 1A12 | AR 1,2 |
| 00000C | 5010 C01C | ST 1,28(,12) |
| 000010 | 07FE | BCR B'1111',14 |
| 000014 | 00000004 | DC F'4' |
| 000018 | 00000006 | DC F'6' |
| 00001C | | DS F |
| | | END ADD2 |

51

Updated ADD2 Demo Program Assembled

| LOC | OBJECT CODE | SOURCE STATEMENT |
|--------|-------------|------------------|
| | | ADD2 CSECT |
| | | LR 12,15 |
| | | L 1,20(,12) |
| | | L 2,24(,12) |
| | | AR 1,2 |
| | | ST 1,28(,12) |
| 00000C | 5010 C01C | BCR B'1111',14 |
| 000010 | 07FE | DC F'4' |
| 000014 | 00000004 | DC F'6' |
| 000018 | 00000006 | DS F |
| 00001C | | END ADD2 |

The next field is fullword aligned, even though this instruction ends two bytes "early"

52

There Must Be an Easier Way!

- What if our program has hundreds or thousands of instructions? Do we have to calculate displacements for every data area?
- Or, what if we change something? Do we have to re-calculate all displacements?
- Fortunately, we don't, or no one would ever use the assembler

53

Use Labels!

- Remember: "Object Code - Nothing Else Matters"
- So, as long as the assembler generates the correct object code, we can do "anything we want" by way of writing source instructions

54

Use Labels!

- We want to use labels - implicit addresses - instead of explicit base and displacement, and let the assembler do the calculations
- We can do this as long as we tell the assembler what base register and base address to use

55

The USING Instruction

- So, instead of writing a base and displacement form of address, we will simply place a label on the storage area definition, then write that label in any instruction operand which references that data
- The assembler must convert the implicit reference to a valid base and displacement

56

The USING Instruction

- We tell the assembler which base register it can use and what base address the register has via the USING assembler instruction (or directive)
- The USING instruction is not executable, and has the following format:

USING baseaddress, baseregister

57

The USING Instruction

- This tells the assembler how to choose the correct base register and how to assign displacements
- USING is your "promise" that at execution time the base register will contain the memory address at which the base address has been loaded

58

The USING Instruction

- Be sure to compare the object code generated by the next version of the program, with the object code generated by the version without USING and labels
- The object code is exactly the same, so the program will execute in exactly the same way
- "Object code - nothing else matters"

59

Demo Program with Labels

- * This program adds two numbers that are taken
- * from WORD1 and WORD2 in the program.
- * The sum is stored in WORD3.

```
ADD2      CSECT
          LR      12,15      Copy addr of 1st inst
          USING   ADD2,12    Tell assembler
          L       1,WORD1    Load 1st no. into R1
          L       2,WORD2    Load 2nd no. into R2
          AR      1,2        Get sum in R1
          ST      1,WORD3    Store sum
          BCR     B'1111',14  Return to caller
WORD1     DC      F'4'       Fullword initially 4
WORD2     DC      F'6'       Fullword initially 6
WORD3     DS      F         Rsrvd only, no init
          END      ADD2
```

60


Demo Program with Labels

| LOC | OBJECT CODE | SOURCE STATEMENT |
|--------|-------------|------------------|
| 000000 | | ADD2 CSECT |
| 000000 | 18CF | LR 12,15 |
| 000002 | | USING ADD2,12 |
| 000002 | 5810 C014 | L 1,WORD1 |
| 000006 | 5820 C018 | L 2,WORD2 |
| 00000A | 1A12 | AR 1,2 |
| 00000C | 5010 C01C | ST 1,WORD3 |
| 000010 | 07FE | BCR B'1111',14 |
| 000014 | 00000004 | WORD1 DC F'4' |
| 000018 | 00000006 | WORD2 DC F'6' |
| 00001C | | WORD3 DS F |
| | | END ADD2 |

61

The Condition Code and Branching

In Which We Learn How to Go Back Where We Came From, or Maybe Go Somewhere Else



62

The Condition Code

- The ADD (A, AR) and SUBTRACT (S, SR) instructions have an additional characteristic not yet mentioned - they set the 2-bit condition code in the following way

| CC | Meaning |
|----|-------------------|
| 0 | Result is 0 |
| 1 | Result is < 0 |
| 2 | Result is > 0 |
| 3 | Overflow occurred |

63

The Condition Code

- Another pair of instructions, COMPARE (C, CR) also set the condition code, but its values are interpreted in a slightly different way

| CC | Meaning |
|----|-----------------------------------|
| 0 | Contents equal |
| 1 | 1st operand val < 2nd operand val |
| 2 | 1st operand val > 2nd operand val |
| 3 | ---- (not set) |

64

The Condition Code

- The condition code is actually two bits of the PSW (bits 34 & 35 in ASSIST/I, bits 18 & 19 in z/Architecture)
- In order to test for all possible combinations of the four CC values, we can use a four-bit mask

Mask B ' x x x x ' (recall B means binary)
CC 0 1 2 3 (CC value tested)

65

BRANCH ON CONDITION

- So a bit mask of B ' 1010 ' will test for condition codes 0 and 2
- The condition code can be tested in only one way - by using the conditional branch instructions BC and BCR

(There are other conditional branch instructions, but they are beyond the scope of this Boot Camp)

66

BRANCH ON CONDITION

- The two forms of BRANCH ON CONDITION are

[RX] label BC B 'mask' , D₂ (X₂ , B₂)

[RR] label BCR B 'mask' , R₂

- The encoded form of each instruction is

[RX] h_{OP} h_{OP} h_{M1} h_{X2} h_{B2} h_{D2} h_{D2} h_{D2}

[RR] h_{OP} h_{OP} h_{M1} h_{R2}

- Note that this has an M₁ subscript instead of the R₁ seen in previous instructions

67

BRANCH ON CONDITION

- If the mask part of the BC or BCR has a 1 in a position corresponding to the current setting of the CC, the next instruction to be executed will be the one whose address is given by the second operand
- Otherwise, the next instruction will be the one whose address is already in the PSW, the one in memory immediately after the branch instruction

68

BRANCH ON CONDITION

- Notice that `BCR B'1111',14` is an unconditional branch to the address in R14 and is the instruction used to end execution of a program
- The mask `B'1111'` matches all four possible CC values

69

A Program Which Tests the Condition Code by Branching

```

MAX      CSECT
         USING MAX,15
         L      1,W1      Get First number
         L      2,W2      Get second number
         CR     1,2       Compare
         BC     B'0010',ONEHIGH Branch if W1 high
         ST     2,W3       Else store second number
         BCR    B'1111',14 Return to caller
ONEHIGH  ST     1,W3       Store first number
         BCR    B'1111',14 Return to caller
W1       DC     F'321'     First number
W2       DC     F'123'     Second number
W3       DS     F         Max of first and second
         END     MAX
    
```

70

A Program Which Tests the Condition Code by Branching

| LOC | OBJECT | CODE | SOURCE | STATEMENT |
|--------|----------|------|---------|--------------------|
| 000000 | | | MAX | CSECT |
| 000000 | | | | USING MAX,15 |
| 000000 | 5810 | F01C | | L 1,W1 |
| 000004 | 5820 | F020 | | L 2,W2 |
| 000008 | 1912 | | | CR 1,2 |
| 00000A | 4720 | F014 | | BC B'0010',ONEHIGH |
| 00000E | 5020 | F024 | | ST 2,W3 |
| 000012 | 07FE | | | BCR B'1111',14 |
| 000014 | 5010 | F024 | ONEHIGH | ST 1,W3 |
| 000018 | 07FE | | | BCR B'1111',14 |
| 00001C | 00000141 | | W1 | DC F'321' |
| 000020 | 0000007B | | W2 | DC F'123' |
| 000024 | | | W3 | DS F |
| | | | | END MAX |

71

X-Instructions and ASSIST//

In Which We Get Data Into and Out of an Assembler Program



72

Character Data

- At this point, we've seen only numeric data, represented as binary fullwords, and created in assemblies as data type F
- But binary data is much too difficult to type, so a different, external, format is used
- In order to work with external data, we will have to know how to represent characters in single bytes of memory

73

Character Data

- There are three standards in current use for representing character data: EBCDIC, ASCII, and Unicode
- We will stick to the EBCDIC representation in these sessions, since
 - It's the only representation known to ASSIST/I
 - It's the representation most common in z/Architecture

74

Some EBCDIC Representations

| | | | | | | | |
|---|----|---|----|---|----|----|----|
| A | C1 | N | D5 | 0 | F0 | . | 4B |
| B | C2 | O | D6 | 1 | F1 | < | 4C |
| C | C3 | P | D7 | 2 | F2 | (| 4D |
| D | C4 | Q | D8 | 3 | F3 | + | 4E |
| E | C5 | R | D9 | 4 | F4 | & | 50 |
| F | C6 | S | E2 | 5 | F5 | ! | 5A |
| G | C7 | T | E3 | 6 | F6 | \$ | 5B |
| H | C8 | U | E4 | 7 | F7 | * | 5C |
| I | C9 | V | E5 | 8 | F8 |) | 5D |
| J | D1 | W | E6 | 9 | F9 | - | 60 |
| K | D2 | X | E7 | | | > | 6E |
| L | D3 | Y | E8 | | | @ | 7C |
| M | D4 | Z | E9 | | | ' | 7D |

| | |
|-------|----|
| blank | 40 |
|-------|----|

75

Character Data

- We can create character data in our programs by using data type C in a DC instruction

```
MESSAGE DC C'1HELLO WORLD!'
```

- The object code generated by this DC is

```
F1C8C5D3D3D640E6D6D9D3C45A
```

76

Character Data

- The 1 in front of the message is a "printer carriage control" character which will cause the message to be printed at the top of a new page
- Other printer carriage control characters are
 - ' ' (blank) - Single space
 - '0' - Double space
 - '-' - Triple space

77

The X-Instructions of ASSIST/I

- For assembler programmers, moving data into and out of a program is a very complex affair, involving numerous operating system I/O "macros"
- For users of ASSIST and ASSIST/I, however, the process is extremely simple and requires only the use of a few non-standard instructions

78

The X-Instructions of ASSIST/I

- In ASSIST and ASSIST/I, these instructions assemble just like "real" instructions, but they are not part of the standard (or any other) instruction set
 - X-instructions are available as "macros" for the High Level Assembler
- The first is XREAD, which reads a record from the input file and places as many bytes as requested (up to 80) starting at the memory address provided; this area is called a "buffer"

79

The XREAD Instruction

■ `label XREAD D1(X1, B1), L2`

D₁(X₁, B₁) is the address of the first byte of the input buffer

L₂ is the number of characters (1 to 80) to be transferred from the input record

- The input record is expected to contain character data

80

The XREAD Instruction

- The XREAD instruction sets the condition code
 - 0 - Read was successful, data placed in memory
 - 1 - end-of-file encountered, no data transferred
 - 2 - [not set]
 - 3 - [not set]

81

The XDECI Instruction

- Numbers are input as characters in the EBCDIC representation and must be converted to binary before we can manipulate them (e.g., ADD or SUBTRACT)
- Input conversion is performed by XDECI

82

The XDECI Instruction

- The XDECI instruction converts an EBCDIC numeric value in memory to a binary numeric value and places it in a register

■ `label XDECI R1, D2(X2, B2)`

R₁ is the register to hold the result

D₂(X₂, B₂) is the memory location at which the search for numeric characters begins

83

The XDECI Instruction Logic - Part 1

1. Start at D₂(X₂, B₂), scan for the first non-blank
2. If the first non-blank is anything but + or - or a decimal digit, set the condition code to 3 and quit
3. Otherwise, 1 to 9 digits are scanned and the resulting number is converted to binary and placed in register R₁

84

The XDECI Instruction Logic - Part 2

4. Register 1 is set to the address of the first non-digit (so register operand R_1 should not be 1!)
5. If ten or more digits are found, register 1 is set to the address of the first subsequent non-digit, the condition code is set to 3, and register R_1 is unchanged

85

The XDECI Instruction Logic - Part 3

- XDECI sets the condition code
 - 0 - The number converted was 0
 - 1 - The number converted was < 0
 - 2 - The number converted was > 0
 - 3 - Non-numeric scanned, or too many digits
- To avoid scanning past the end of the buffer, include a "scan stopper":

| | | | |
|-------|----|-------|-------------------|
| INPUT | DS | CL80 | Input Buffer |
| | DC | C '*' | Non-digit stopper |

86

The XDECO Instruction

- The XDECO instruction converts a binary numeric value in a register to an EBCDIC numeric value in memory (action opposite that of XDECI)
- Positive numbers appear with no sign, but negative numbers appear with a leading minus sign

87

The XDECO Instruction

- `label XDECO $R_1, D_2(X_2, B_2)$`

R_1 is the register containing the binary number to convert

$D_2(X_2, B_2)$ is the beginning memory location, usually within a print buffer, to store the EBCDIC number, right-justified, occupying 12 bytes

88

The XPRNT Instruction

- The XPRNT instruction will print one line of output of maximum length 133 characters, including the carriage control (CC)

label XPRNT D₁(X₁,B₁),L₂

D₁(X₁,B₁) is the address of the first byte of the output buffer (the CC character)

L₂ is the number of characters (including carriage control) to be transferred from memory to the print line

89

Example With X-Instructions (1 of 2) [demob.asm]

```
* THIS PROGRAM READS DATA CARDS EACH HAVING TWO
* NUMBERS. THE SUM OF THE NUMBERS IS PRINTED.
*
SUMUP      CSECT
           USING SUMUP,15
*
           XPRNT HEADING,28      PRINT PAGE HDR
           XREAD CARD,80         READ 1ST CARD
*
CHECKEOF BC B'0100',EXIT      BR ON EOF
*
           XDECI 2,CARD          ASSUME BOTH NUMS
           XDECI 3,0(,1)         ARE VALID
*
           AR      2,3           CALCULATE THE SUM
```

90

Example With X-Instructions (2 of 2) [demob.asm]

```
           XDECO 2,OUTPUT      PRINTABLE FORM
*                                     INTO PRINT LINE
           XPRNT CRG,13        PRINT THE SUM
*                                     AFTER SINGLE SPACE
           XREAD CARD,80      TRY ANOTHER READ
BC      B'1111',CHECKEOF GO CHECK FOR EOF
*
EXIT    BCR      B'1111',14    TERMINATE PROGRAM
*
CARD    DS      CL80          INPUT BUFFER
*
CRG     DC      C' '          SINGLE SPACE CC
OUTPUT  DS      CL12          SUM GOES HERE
HEADING DC      C'1THIS IS THE OUTPUT OF SUMUP'
END     SUMUP
```

91

What's Next?

- Tomorrow, we we will construct program loops
- Also, we will see one of the simplest and most challenging machine instructions, the LOAD ADDRESS instruction (when you are comfortable with addresses, you will have a good understanding of assembler)
- We will also do more arithmetic (multiplication and division) if we have time

92