


RMF – The Latest and Greatest

Peter Muench (pmuench@de.ibm.com)
IBM Corporation

Monday, August 4, 2014
Session 15710



Copyright (c) 2014 by SHARE Inc.  Except where otherwise noted, this work is licensed under <http://creativecommons.org/licenses/by-nc-sa/3.0/>

Trademarks



The following are trademarks of the International Business Machines Corporation in the United States, other countries, or both.

Not all common law marks used by IBM are listed on this page. Failure of a mark to appear does not mean that IBM does not use the mark nor does it mean that the product is not actively marketed or is not significant within its relevant market.

Those trademarks followed by ® are registered trademarks of IBM in the United States; all others are trademarks or common law marks of IBM in the United States.

For a complete list of IBM Trademarks, see www.ibm.com/legal/copytrade.shtml:

*, AS/400®, e business(logo)®, DBE, ESCO, eServer, FICON, IBM®, IBM (logo)®, iSeries®, MVS, OS/390®, pSeries®, RS/6000®, S/30, VM/ESA®, VSE/ESA, WebSphere®, xSeries®, z/OS®, zSeries®, z/VM®, System i, System i5, System p, System p5, System x, System z, System z9®, BladeCenter®

The following are trademarks or registered trademarks of other companies.

Adobe, the Adobe logo, PostScript, and the PostScript logo are either registered trademarks or trademarks of Adobe Systems Incorporated in the United States, and/or other countries.

Cell Broadband Engine is a trademark of Sony Computer Entertainment, Inc. in the United States, other countries, or both and is used under license therefrom.

Java and all Java-based trademarks are trademarks of Sun Microsystems, Inc. in the United States, other countries, or both.

Microsoft, Windows, Windows NT, and the Windows logo are trademarks of Microsoft Corporation in the United States, other countries, or both.

Intel, Intel logo, Intel Inside, Intel Inside logo, Intel Centrino, Intel Centrino logo, Celeron, Intel Xeon, Intel SpeedStep, Itanium, and Pentium are trademarks or registered trademarks of Intel Corporation or its subsidiaries in the United States and other countries.

UNIX is a registered trademark of The Open Group in the United States and other countries.

Linux is a registered trademark of Linus Torvalds in the United States, other countries, or both.

ITIL is a registered trademark, and a registered community trademark of the Office of Government Commerce, and is registered in the U.S. Patent and Trademark Office.

IT Infrastructure Library is a registered trademark of the Central Computer and Telecommunications Agency, which is now part of the Office of Government Commerce.

* All other products may be trademarks or registered trademarks of their respective companies.

Notes:

Performance is in Internal Throughput Rate (ITR) ratio based on measurements and projections using standard IBM benchmarks in a controlled environment. The actual throughput that any user will experience will vary depending upon considerations such as the amount of multiprogramming in the user's job stream, the I/O configuration, the storage configuration, and the workload processed. Therefore, no assurance can be given that an individual user will achieve throughput improvements equivalent to the performance ratios stated here.

IBM hardware products are manufactured from new parts, or new and serviceable used parts. Regardless, our warranty terms apply.

All customer examples cited or described in this presentation are presented as illustrations of the manner in which some customers have used IBM products and the results they may have achieved. Actual environmental costs and performance characteristics will vary depending on individual customer configurations and conditions.

This publication was produced in the United States. IBM may not offer the products, services or features discussed in this document in other countries, and the information may be subject to change without notice. Consult your local IBM business contact for information on the product or services available in your area.


All statements regarding IBM's future direction and intent are subject to change or withdrawal without notice, and represent goals and objectives only.

Information about non-IBM products is obtained from the manufacturers of those products or their published announcements. IBM has not tested those products and cannot confirm the performance, compatibility, or any other claims related to non-IBM products. Questions on the capabilities of non-IBM products should be addressed to the suppliers of those products.

Prices subject to change without notice. Contact your IBM representative or Business Partner for the most current pricing in your geography.



RMF Product Overview



- z/OS Resource Measurement Facility (RMF) is an optional priced feature of z/OS. It supports installations in performance analysis, capacity planning, and problem determination. For these disciplines, different kinds of data collectors are needed:
 - Monitor I long term data collector for all types of resources and workloads. The SMF data collected by Monitor I is mostly used for capacity planning and performance analysis
 - Monitor II snap shot data collector for address space states and resource usage. A subset of Monitor II data is also displayed by the IBM SDSF product
 - Monitor III short-term data collector for problem determination, workflow delay monitoring and goal attainment supervision. This data is also used by the RMF PM Java Client and the RMF Monitor III Data Portal
- Data collected by all three gatherers can be saved persistently for later reporting (SMF records or Monitor III VSAM datasets)
- While Monitor II and Monitor III are realtime reporters, the RMF Postprocessor is the historical reporting function for Monitor I data
- One of the key components for the sysplex wide access of Monitor III data is the RMF Distributed Data Server (DDS). Beginning with RMF for z/OS 1.12, DDS supports HTTP requests to retrieve RMF Postprocessor data from a selection of RMF Postprocessor reports. Since the requested data are returned as XML document, a web browser can act as Data Portal to RMF Postprocessor data.
- Since z/OS 1.12 there's another exploiter of the RMF DDS data: The z/OSMF Resource Monitoring plugin of the z/OS Management Facility.
- RMF for z/OS 1.13 enhances the DDS layer with a new component:
 - RMF XP is the new solution for Cross Platform Performance Monitoring
 - Provides a seamless performance monitoring for all operating systems running on the IBM zEnterprise Bladecenter Extension.

z/OS V2R1 RMF Content at a Glance



- ▶ IBM zEnterprise EC12 Support
 - ⇒ Statistics for Flash Memory and Pageable Large Pages
 - ⇒ Support of Coupling Facility Flash Memory
 - ⇒ z Enterprise Data Compression Express Reporting (zEDC)
 - ⇒ Shared Memory Communication Reporting (SMC-R)
 - ⇒ Support of I/O Interrupt Delay Time Facility
 - ⇒ Extended Infiniband Link Reporting
 - ⇒ Support of Crypto Express4 Card
 - ⇒ Warning Track Interruption Facility Statistics
- ▶ Exploitation of System z Integrated Information Processors
 - ⇒ zIIP Usage Option for Monitor III Gatherer
- ▶ Postprocessor XML formatted Reports
 - ⇒ Transition to XML Format almost complete
 - ⇒ Advanced Sorting and Filtering Capabilities
- ▶ RMF XP Enhancements
 - ⇒ Performance Monitoring of Windows Images
 - ⇒ SMF Type 104 Recording for all Platforms
- ▶ z/OSMF Resource Monitoring
 - ⇒ Context sensitive Application Linkage to WLM
 - ⇒ Windows Support
 - ⇒ Historical Reporting & Spreadsheet Export



4

In accordance with the availability of new z/OS releases and new hardware functionality, the capabilities of RMF are enhanced consecutively


- Together with the new zEnterprise EC12 servers RMF provides the following support:
 - Usage statistics for Pageable Large Pages and Storage Class Memory in various RMF Postprocessor, Monitor II and Monitor III reports.
 - RMF Support for CFCC Storage Class Memory exploitation.
 - New statistics to report PCIE based data compression and shared memory communication.
 - Reporting of new I/O Interrupt Delay Time
 - Additional channel path information for channel paths of type CIB or CFP
 - Support of Crypto Express4 Card and the Warning-Track-Interruption-Facility
- With z/OS V2R1 RMF, the Monitor III Data Gatherer (RMFGAT) can partially offload work to zIIP processors
- Starting with z/OS V1R11, a subset of RMF Postprocessor reports can be generated in XML format. The new format provides:
 - Browser based, state-of-the-art display of SMF Type 7x data
 - Standardized format for access to performance data via XML parsing
- RMF for z/OS V2R1 completed the work on enabling Postprocessor reports for XML format output and provides sorting and filtering capabilities when the XML report is displayed in a web browser.
- RMF XP is the new solution for Cross Platform Performance Monitoring
 - Provides a seamless performance monitoring for all operating systems running on the IBM zEnterprise BladeCenter Extension.
 - z/OS V2R1 enhancements :
 - Support to collect and display performance data from Windows images running on system x.
 - Persistent recording of cross platform performance data in the new SMF record type 104.
- z/OSMF Resource Monitoring enhancements:
 - Context sensitive Application Linkage to z/OSMF WLM plugin
 - Display new Windows performance data collected by RMF XP
 - Display historical data and export the data as CSV for spreadsheet usage.

zEC12 – Flash Express




What is Flash Express?

- ▶ New memory hierarchy of the zSeries family
- ▶ Delivers tier within the fast Solid State Drive (SSD) technology
- ▶ Also denoted as Storage Class Memory (SCM)
- ▶ Integrated on PCI Express attached RAID 10 Cards
 - ⇒ Packaged as two card pair
 - ⇒ Each card holds 1.4 TB of memory per mirrored card pair
 - ⇒ Maximum value of four card pairs delivers up to 5.6 TB of memory



How is Flash Express exploited by z/OS ?

- ▶ Designed for improved paging performance
- ▶ Compelling addition to traditional auxiliary storage
- ▶ Supports Pageable Large Pages, e.g. with DB2 and Java workloads
- ▶ Eliminates delays from SVC or standalone dump processing
- ▶ Provides overflow capability for MQSeries list structures



5

- The Flash Express feature (FC 0402) of IBM zEnterprise EC12 (zEC12) server is a new memory hierarchy of the zSeries family
- It consists of non-volatile storage using solid state devices on a PCIe card form factor.
- Flash Express implements a new tier of memory, called Storage Class Memory (SCM).
- Flash Express Cards are installed in pairs, which provides mirrored data to ensure a high level of availability and redundancy.
- In each Flash Express card, the data is stored in four solid-state disks in a RAID configuration. If a solid-state disk fails, the data are reconstructed dynamically. The cards in a pair mirror each other over a pair of cables, in a RAID 10 configuration. If either card fails, the data is available on the other card.
- Each Flash Express card has a capacity of 1.4 TB of usable storage.
- A maximum of four pairs of cards can be installed on a zEC12, for a maximum capacity of 5.6 TB of storage.
- Flash Memory is assigned to partitions like Main Memory from the allocation panel on the zEC12 Service Element (SE)
- z/OS can use Flash Express storage as Storage Class Memory (SCM) for paging.
- Flash Express helps to improve paging performance since page access time from Flash Express is faster than from DASD devices.
- The z/OS paging subsystem can work with a mix of Flash Express storage and External Disk.
- z/OS detects whether Flash Express storage is assigned to the LPAR and will try to page to Flash Express before using paging datasets on DASD.
- In combination with the new pageable 1MB pages, Flash Express helps to improve the performance of DB2 and Java workloads.
- Latency delays in SVC or standalone dump processing caused by page-ins from DASD can be significantly reduced by Flash Express.
- The Coupling Facility can exploit SCM as overflow capacity for list structure data. This functionality can be used by MQSeries to avoid structure-full conditions.

zEC12 – Flash Memory & Pageable Large Pages RMF Support



- ▶ New Storage Class Memory (SCM) statistics in
 - ⇒ RMF Postprocessor Paging Activity report
 - ⇒ RMF Postprocessor Page Data Set Activity (PAGE SP) report
 - ⇒ RMF Monitor II Page Data Set Activity (PG SP) report
- ▶ New statistics for Pageable Large Pages in
 - ⇒ RMF Postprocessor Paging Activity report
 - ⇒ RMF Postprocessor Virtual Storage Activity (VSTOR) report
 - ⇒ RMF Monitor III Storage Memory Objects (STORM) report



6 Complete your session evaluations online at www.SHARE.org/Pittsburgh-Eval

- RSM web deliverable (FMID JBB778H) exploits the new flash memory by introducing a new tier of memory called Storage Class Memory (SCM) that is used by the paging subsystem.
- In addition to support for the existing large (1 MB) pages and frames, zEC12 supports **pageable** large pages when SCM is configured and allocated to z/OS.
- With RMF new function APAR OA38660, RMF provides the SCM and Pageable Large Pages support for z/OS 1.13
- The support enhances RMF Postprocessor, Monitor II and Monitor III reports with various new statistics for SCM and pageable large pages.

zEC12 – Flash Memory & Pageable Large Pages...



⇒ New SCM statistics in the FRAMES AND SLOT COUNTS section of the RMF Postprocessor Paging Activity report

The number of shared pages backed on SCM

SHARED FRAMES	TOTAL SLOTS	CENTRAL STORAGE	FIXED TOT	FIXED BEL	AUX DASD	AUX SCM
MIN	7,937	44	30	0	13	0
MAX	7,937	44	30	0	13	0
AVG	7,937	44	30	0	13	0

LOCAL PAGE DATA SET SLOTS	TOTAL	AVAILABLE	BAD	NON-VIO	VIO
MIN	5,399,997	4,269,302	0	1,128,251	0
MAX	5,399,997	4,271,746	0	1,130,695	0
AVG	5,399,997	4,269,838	0	1,130,159	0

SCM PAGING BLOCKS	TOTAL	AVAILABLE	BAD	IN-USE
MIN	0	0	0	0
MAX	0	0	0	0
AVG	0	0	0	0

System wide statistics of 4K SCM paging blocks as: Total, Available, Unavailable and Used 4K blocks

- The Frame and Slot Counts section of the RMF Postprocessor Paging Activity report is enhanced to report a new SCM Paging Block with statistics about the system wide usage of SCM.
- If SCM is not available the SCM Paging Block section is not shown.
- The SHARED FRAMES statistics are extended with a new metric to display the number of shared pages that are backed on SCM.

zEC12 – Flash Memory & Pageable Large Pages...



⇒ New SCM and Large Pages statistics in the MEMORY OBJECTS section of the RMF Postprocessor Paging Activity report

PAGING ACTIVITY

OPT = IEAOPT00

LFAREA SIZE = 209715200

MEMORY OBJECTS AND HIGH VIRTUAL STORAGE FRAMES

MEMORY OBJECTS

COMMON

SHARED

1 MB

MIN

53

1

1

MAX

56

1

4

AVG

54

1

2

System wide usage of Large Frame Area (Fixed Frames and Pageable Large Frames)

1 MB FRAMES

FIXED

PAGEABLE

TOTAL

AVAILABLE

IN-USE

TOTAL

AVAILABLE

IN-USE

MIN

200

80

30

560

496

57

MAX

200

170

120

560

503

64

AVG

200

136

64

560

501

59

HIGH SHARED FRAMES

TOTAL

MIN

136902.1M

MAX

136902.1M

AVG

136902.1M

CENTRAL STORAGE

206

206

206

AUX DASD

0

0

0

AUX SCM

0

0

0

HIGH COMMON FRAMES

TOTAL

MIN

17301504

MAX

17301504

AVG

17301504

Size of high virtual shared and common area in units of 4KB pages

AUX DASD

0

0

0

AUX SCM

0

0

0

Number of auxiliary storage slots used for high virtual common and shared memory pages that are backed on SCM storage

System wide usage of Large Frame Area (Fixed Frames and Pageable Large Frames)

Size of high virtual shared and common area in units of 4KB pages

Number of auxiliary storage slots used for high virtual common and shared memory pages that are backed on SCM storage

- The Memory Objects and High Virtual Storage Frames section of the Postprocessor Paging Activity report now shows values for both fixed and pageable 1 MB frames
- New statistics for High Shared and High Common Frames:
 - TOTAL: Size of high virtual shared and common area in units of 4 KB pages.
 - AUX SCM: Number of auxiliary storage slots used for high virtual shared and common pages that are backed on SCM storage.
- The number of auxiliary storage slots on DASD are added to complement the new information on frames and page data set slots for SCM data blocks.

zEC12 – Flash Memory & Pageable Large Pages...



⇒ New SCM statistics RMF Postprocessor Page Data Set Activity report

PAGE DATA SET ACTIVITY														
z/OS V1R13					SYSTEM ID TRX2					DATE 03/10/2012			INTERVAL 15.00.012	
										TIME 13.00.00			CYCLE 1.000 SECONDS	
NUMBER OF SAMPLES = 900					PAGE DATA SET AND SCM USAGE									

PAGE									%	PAGE			V	
SPACE	VOLUME	DEV	DEVICE	SLOTS	----	SLOTS	USED	---	BAD	IN	TRANS	NUMBER	PAGES	I
TYPE	SERIAL	NUM	TYPE	ALLOC	MIN	MAX	AVG	SLOTS	USE	TIME	IO	REQ	XFER'D	O
PLPA	TRX2PP	D406	33903	71999	16851	16851	16851	0	0.00	0.000	0	0	0	PAGE.VTRX2PP.PLPA
COMMON	TRX2PP	D406	33903	35999	34	34	34	0	0.00	0.000	0	0	0	PAGE.VTRX2PP.COMMON
LOCAL	TRX2P1	D506	33903	593999	0	0	0	0	0.00	0.000	0	0	0	PAGE.VTRX2P1.LOCAL1
SCM	N/A	N/A	N/A	131072	43151	43151	43151	0	0.00	0.000	0	0	0	N/A

System wide statistics of
4K SCM paging block usage and
SCM paging activity



- The Postprocessor Page Data Set Activity report displays SCM Paging Block information for page data set of type SCM.

zEC12 – Flash Memory & Pageable Large Pages...



⇒ Statistics for Fixed Large Memory Objects in RMF Postprocessor Virtual Storage Activity report

VIRTUAL STORAGE ACTIVITY										PAGE	4
z/OS V2R1		SYSTEM ID SYS3				DATE 11/25/2011		INTERVAL 14.59.996			
		RPT VERSION V2R1 RMF				TIME 05.30.00		CYCLE 1.000 SECONDS			
PRIVATE AREA DETAIL											
JOB NAME - JES2		MEMORY LIMIT - 20000M									
...											
MEMORY ALLOCATION IN HIGH VIRTUAL MEMORY (ABOVE 2GB)											
BYTES	MIN		MAX		AVG		PEAK				
PRIVATE	1.823T	05.31.52	22.41T	05.50.36	11.51T	131.8T					
SHARED	485.1M	05.31.52	1822M	05.58.15	552.2M	1.333T					
COMMON	885.1M	05.31.52	1.22M	05.56.15	1.2T	1.927T					
MEMORY OBJECTS											
PRIVATE	80	05.31.52	160	05.35.52	110						
SHARED	20	05.31.52	70	05.35.52	23						
COMMON	30	05.31.52	60	05.35.52	44						
1 MB	20	05.31.52	70	05.35.52	25						
FRAMES (1 MB)											
FIXED	4	05.31.52	26	05.35.52	21						
PAGEABLE	4	05.31.52	26	05.35.52	21						

Decomposition into
Fixed and Pageable Large Pages

Decomposition into
Fixed and Pageable Large Pages

10 Complete your session evaluations online at www.SHARE.org/Pittsburgh-Eval

Pittsburgh 2014

- The Private Area Detail section of the RMF Postprocessor VSTOR report displays the MIN, MAX, and AVG values for the number of 1 MB frames that are used by **FIXED** and **PAGEABLE** memory objects that are owned by the reported address space.
- The PAGEABLE value also includes 1 MB frames that are used by DREF memory objects.

zEC12 – Flash Memory & Pageable Large Pages...

New Large Page statistics in RMF Monitor III STORM report

RMF V1R13 Storage Memory Objects

Samples: 60 System: TRX1 Date: 04/18/12 Time: 10.56.00

---MemObj---		---Frames---		System Summary		---1MB Fixed---		---1MB Pageable---	
Shared	1	Shared	206	-1MB MemObj-		Total	200	Initial	560
Common	51	Common	24554	Total	4	Common	76	Dynamic	0
		%Used	8.3	Common	3	%Used	52.8	%Used	10.5

Jobname	C	Class	ASID	Total	Comm	Shr	1 MB	Fixed	Pgable	Total	Comm	Shr
OMVS	S	SYSTEM	0007	15	0	0	0	0	12	1351M	0	0
COMM641M	B	JESLOW	0035	3	1	0	1	30	0	32.0M	30.0M	0
STOR641M	B	JESLOW	0054	3	0	0	1	30	0	32.0M	0	0

System wide usage of Large Frame Area (Fixed Frames) and Pageable Large Frames

Average number of 1 MB frames that are used by pageable and DREF memory objects owned by this address space

11 Complete your session evaluations online at www.share-pittsburgh.com

New and changed System Summary fields in Monitor III Storage Memory Objects (STORM) report:

Frames	%Used	Percentage of high virtual common storage used by the system.
1MB MemObj	Common	Average number of fixed memory objects that are allocated in high virtual common storage and can be backed in 1 MB frames. This value includes the memory objects that cannot be attributed to an address space.
1MB Fixed	Total	Total number of 1 MB frames that can be used by fixed memory objects. This value is equal to the size of the Large Frame Area in megabytes.
	Common	Average number of 1 MB high virtual common memory pages fixed in central storage. This value includes the pages that cannot be attributed to an address space or have not been freed during address space termination.
	%Used	Percentage of 1 MB frames that are used by fixed memory objects in the Large Frame Area regardless of whether the frames are actually used for 1 MB pages or used to satisfy 4K page requests on a constraint system.
1MB Pgable	Initial	Number of 1 MB frames that can be used by pageable and DREF memory objects. This value is calculated by the system at IPL time.
	Dynamic	Average number of 1 MB frames in the LFAREA that were used to satisfy 1 MB pageable page requests.
	%Used	Percentage of 1 MB frames that are used by pageable and DREF memory objects, regardless of whether the frames are actually used for 1 MB pages or used to satisfy 4K space requests on a constrained system.

New and changed Address Space related fields:

1MB Frames	Fixed	Average number of 1 MB frames in the Large Frame Area owned by this address space. Frames that are used to satisfy 4K space requests on a constrained system are not included.
	Pgable	Average number of 1 MB frames that are used by pageable and DREF memory objects owned by this address space. Pageable memory objects that have been fixed after allocation, are also included. Frames that are either used by common 1 MB pages or to satisfy 4K space requests on a constrained system are not included.

zEC12 – Coupling Facility Flash Memory




► Coupling Facility Exploitation of SCM

- ⇒ Allows migration of MQSeries Shared Queue objects to flash memory when structure utilization exceeds threshold
- ⇒ MQ objects fetched back to real CF Storage when requested
- ⇒ Provides overflow capability for MQ Shared Queues to handle workload peaks

► New CF SCM statistics in

- ⇒ RMF Postprocessor Coupling Facility Activity (CF) report
- ⇒ RMF Monitor III Coupling Facility Overview (CFOVER) report
- ⇒ RMF Monitor III Coupling Facility Activity (CFACT) report



12 Complete your session evaluations online at www.SHARE.org/Pittsburgh-Eval

- Currently, the CF is a pure “real memory” system – all CF structures are allocated and backed entirely by real memory in the CF image. There is no storage hierarchy, hence no paging, no virtual storage, no disk I/O at all.
- With CFCC Level 19 the CF exploits internal flash memory for the purpose of migrating structure objects out to flash memory when the number of objects exceeds a calculated threshold and fetching them back into main CF storage when requested.
- Requires z/OS 2.1, or z/OS 1.13 with new function APAR OA40747
- Initially the CF Flash exploitation is targeted for MQ shared queues application structures.
- With RMF new function APAR OA40515, RMF provides the support for CFCC Storage Class Memory exploitation on the IBM zEnterprise EC12 (zEC12) server on z/OS 2.1 and z/OS 1.13.
- The support enhances RMF Postprocessor and Monitor III reports with various new CF SCM statistics.

zEC12 – Coupling Facility Flash Memory...

RMF Postprocessor Coupling Facility Activity Report:

⇒ SCM statistics in STORAGE SUMMARY section

System wide
SCM statistics

STORAGE SUMMARY				
	ALLOC SIZE	% OF CF STORAGE	----- DUMP SPACE ----- % IN USE MAX % REQUESTED	
TOTAL CF STORAGE USED BY STRUCTURES	3344M	3.3		
TOTAL CF DUMP STORAGE	6M	0.0	0.0	0.0
TOTAL CF AUGMENTED SPACE	32M	0.0		
TOTAL CF STORAGE AVAILABLE	98536M	96.7		

TOTAL CF STORAGE SIZE	101918M			
	ALLOC SIZE	% ALLOCATED		
TOTAL CONTROL STORAGE DEFINED	101918M	3.3		
TOTAL DATA STORAGE DEFINED	0K	0.0		
	ASSIGNED	% IN USE	SUM MAX SCM	
TOTAL CF STORAGE CLASS MEMORY	524288M	1.0	16384M	

Augmented space:
- Total allocated in bytes
- % of CF storage

CF SCM space:
- Assigned capacity in bytes
- Capacity used
- Max possible SCM usage derived
from current CFRM policy

- The 'STORAGE SUMMARY' section of the RMF Postprocessor Coupling Facility report is enhanced by SCM statistics about SCM space and augmented space usage.

TOTAL CF AUGMENTED SPACE:


ALLOC SIZE Total amount of CF storage used by all structures as augmented space (in bytes).
% OF CF STORAGE Percentage of CF storage used by all structures as augmented space.

TOTAL CF STORAGE CLASS MEMORY:

ASSIGNED Total CF SCM. This is the amount of SCM that may be concurrently used as structure extensions. Storage is assigned in increments of 4K bytes.
% IN USE Percentage of SCM that is in use by all structures of the coupling facility.
SUM MAX SCM Sum of the SCM maxima defined for all structures of the coupling facility.

zEC12 – Coupling Facility Flash Memory...

RMF Monitor III CFACT Report: Structure Details Pop-up



15

- With the RMF CF SCM support the Monitor III CFACT structure details pop-up window now provides the percentage of CF storage used by structure in new field:

% of CF Storage The percentage of the total coupling facility storage allocated to this structure.

- For LIST structures that can use SCM storage extension the details pop-up window also shows SCM related statistics:

Augmented Space	Est Max	Estimated maximum amount of augmented space in bytes that can be assigned for this structure.
	% Used	Percentage of maximum augmented space that is in use by the structure.
SCM Space	Maximum	Maximum amount of SCM in bytes that this structure can use.
	% Used	Percentage of maximum SCM space that is in use by the structure.
SCM List Entries	Est Max	Estimated maximum number of list entries that can reside in SCM for the structure.
	Current	Number of existing structure list entries that reside in SCM.
SCM List Elements	Est Max	Estimated maximum number of list elements that can reside in SCM for the structure.
	Current	Number of existing structure list elements that reside in SCM.

zEC12 - Data Compression Express




- ▶ The z Enterprise Data Compression (zEDC) Express offering provides a low-cost data compression to z/OS system services and applications.
- ▶ Compression can be requested on
 - ⇒ Dataset level via COMPACTION option in the SMS data class
 - ⇒ System level via COMPRESS parameter in SYS1.PARMLIB(IGDSMSxx)
- ▶ Exploiters will see the following benefits
 - ⇒ Reduced disk space
 - ⇒ Increased performance for reading and writing compressed data
- ▶ The zEDC is implemented as a Peripheral Component Interconnect Express (PCIe) device that can be installed on zEC12 GA2 and zBC12.
- ▶ The compression function is provided via FPGA firmware. Other functions (also denoted as personality) may follow.
- ▶ You can install up to eight devices in a single machine where each device is sharable by up to 15 LPARs.



zEC12 - Shared Memory Communication

- ▶ Shared Memory Communication via Remote Direct Memory Access (SMC-RDMA or SMC-R) is a zEC12 feature that provides high performance CPC to CPC communication
- ▶ SMC-R actually offers the benefits of HiperSockets across processor boundaries. It takes advantage of high speed protocols and direct memory placement of data.
- ▶ SMC-R is totally transparent to applications.
- ▶ SMC-R is implemented as a Peripheral Component Interconnect Express (PCIe) device, also denoted RoCE adapter card (RDMA over Converged Ethernet)

- 
- ✓ Common PCIe form factor
 - ✓ Common API for retrieval of activity statistics



zEC12 - Obtain PCIe Information by Command

- ▶ Use the console command **D PCIE** for general status information

PCIe Started Task

```
D PCIE
IQP022I 12.06.02 DISPLAY PCIE 970
PCIE      0013 ACTIVE
PFID  DEVICE TYPE NAME      STATUS  ASID  JOBNAME  PCHID VFN
0001  Hardware Accelerator  ALLC   0014  FPGHWAM  0380  0001
0020  10GbE RoCE           ALLC   00DE  VTAM     038C
0021  10GbE RoCE           CNFG           0380
0011  Hardware Accelerator  ALLC   0014  FPGHWAM  05C4  0001
```

PCIe Function ID

Owner Name

Physical Channel Identifier

Virtual Function Number

- ▶ Use the console command **D PCIE,PFID=xxx** for adapter details

```
D PCIE,PFID=001
IQP024I 12.10.53 DISPLAY PCIE 521
PCIE      0013 ACTIVE
PFID  DEVICE TYPE NAME      STATUS  ASID  JOBNAME  PCHID VFN
0001  Hardware Accelerator  ALLC   0014  FPGHWAM  0380  0001
CLIENT ASIDS: NONE
Application Description: zEDC Express
Device State: Ready
Adapter Info - Relid: 000000 Arch Level: 03
                Build Date: 06/28/2013 Build Count: 03
```


zEC12 - RMF Postprocessor PCIE Activity Report



- ▶ RMF Monitor III Data Gatherer collects PCIe performance statistics frequently and writes new SMF Record Type 74 Subtype 9
- ▶ The new RMF Postprocessor PCIE Activity Report provides detailed information about PCIe Express based functions.
Currently supported functions are:
 - ⇒ z Enterprise Data Compression (zEDC)
 - ⇒ Shared Memory Communication via RDMA (SMC-R)
- ▶ New suboption PCIE | NOPCIE for Postprocessor REPORTS option
- ▶ Only available in XML format

RMF Postprocessor Duration Report [System SYSB] : PCIE Activity Report

RMF Version : z/OS V2R1 SMF Data : z/OS V2R1

Start : 11/14/2013-17.45.00 End : 11/14/2013-18.00.00 Interval : 000:15:00 hours

RoCE

Basic PCIe Metrics, e.g.
PCI Load/Store and
DMA Operations

▼ General PCIE Activity

Function ID	Function PCHID	Function Name	Function Type	Function Status	Owner Job Name	Owner Address Space ID	Function Allocation Time	PCI Load Operations Rate	PCI Store Operations Rate	PCI Store Block Operations Rate	Refresh PCI Translations Operations Rate	DMA Address Space Count	DMA Read Data Transfer Rate	DMA Write Data Transfer Rate
0010	03BC	10GbE RoCE	15B31003	Allocated	VTAM	002A	900	0.921	9499	0	0.104	1	1993	21.8
0040	05EC	10GbE RoCE	15B31003	Allocated	VTAM	002A	900	0.923	9544	0	0.104	1	3434	12.6

19 Complete your session evaluations online at www.SHARE.org/Pittsburgh-Eval

- The PCIe performance data is collected by RMF Monitor III and stored in the new SMF 72 subtype 9.
- There is no RMF data gathering option. Data gathering is controlled by the SMF 72-9 setting in the active SMF parmlib member ERBSMFxx. Use TYPE/NOTYPE in the SMFPRMxx parmlib member to enable/disable the data gathering.
- Specify suboption PCIE in the RMF Postprocessor REPORTS control statement to create the new Postprocessor **PCIE Activity Report**.
- The PCIE Activity Report is only available in XML format.
- XML report can be created and displayed
 - via RMF Data Portal (SMF data from SMF buffer only)
 - via Spreadsheet Reporter (any SMF source)
- There is another option to display the SDELAY report in a web browser:
 - Download the XML output created by the RMF Postprocessor JOB to the toolkit directory provided with the RMF Postprocessor XML Toolkit
 - Open the report in the toolkit directory with your web browser.
- The PCIE Activity Report has up to three sections
 1. General PCIE Activity section
 - Measurements for all PCIe functions
 - Data rates for PCI operations transferring data blocks from z/OS to the PCIe function
 - Direct memory access (DMA) read/write counters
 2. Hardware Accelerator Activity section
 - Common accelerator request statistics: Queue Time, Execution Time and Request Rate
 3. Hardware Accelerator Compression Activity
 - Measurements for zEDC
 - Compression related statistics:
 - Number of compressed bytes in and out
 - Number of decompressed bytes in and out
 - Buffer usage

zEC12 - RMF Postprocessor PCIE Activity Report



▼ General PCIE Activity

Function ID	Function PCHID	Function Name	Function Type	Function Status	Owner Job Name	Owner Address Space ID	Function Allocation Time	PCI Load Operations Rate	PCI Store Operations Rate	PCI Store Block Operations Rate	Refresh PCI Translations Operations Rate	DMA Address Space Count	DMA Read Data Transfer Rate	DMA Write Data Transfer Rate
00A0	03C0	Hardware Accelerator	1014044B	Allocated	FPGHWAM	0012	14400	0	0.054	0	<0.01	1	21.8	21.2
00B0	0500	Hardware Accelerator	1014044B	Allocated	FPGHWAM	0012	14400	0	0.054	0	<0.01	1	1.19	1.19

zEDC

Common Request Statistics across all Personalities (Compression and future Personalities)

▼ Hardware Accelerator Activity

Function ID	Time Busy %	Request Execution Time	Std Dev for Request Execution Time	Request Queue Time	Std Dev for Request Queue Time	Request Size	Transfer Rate Total
00A0	0.002	27.7	4.77	462	70.0	69.6	0.056
00B0	0.002	28.6	5.07	487	39.8	69.6	0.059


Compression related Statistics

▼ Hardware Accelerator Compression Activity

Function ID	Compression Request Rate	Compression Throughput	Compression Ratio	Decompression Request Rate	Decompression Throughput	Decompression Ratio	Buffer Pool Size	Buffer Pool Utilization
00A0	0.140	0.008	5.03	0.665	0.008	0.198	15360	0
00B0	0.139	0.008	5.03	0.713	0.008	0.198	15360	0



zEC12 – I/O Interrupt Delay Time



- ▶ Interrupt Delay time measures the time between when the I/O completes and z/OS issues the TSCH instruction to retrieve the results.
- ▶ How long does it take for z/OS to see and process the interrupt after I/O completes ?

- The response time that is reported for a device is the sum of IOS QUEUE time, PENDING time, CONNECT time and DISCONNECT time.
- However, there is another response time component that was not measured and reported but impacts the overall I/O response time as seen by the application:
 - ⇒ The I/O Interrupt Delay time
- Interrupt Delay time is the time between when the I/O completes and z/OS issues the TSCH instruction to retrieve the results. In other words:
How long does it take for z/OS to see and process the interrupt after I/O completes ?

zEC12 – I/O Interrupt Delay Time

- ▶ I/O interrupt delay time (aka I/O elongation) occurs when an I/O is delayed due to
 - 🚫 a non-dispatched LPAR
 - 🚫 the lack of an interrupt enabled CP
- ▶ I/O interrupt delay time is NOT included in the I/O response time
- ▶ I/O interrupt delay time could NOT be measured in the past
- ▶ High ratios of interrupts handled via TPI (Test Pending Interrupt) are an indicator for significant I/O elongation



▼ CPU Activity

CPU : 2817 Model : 729 H/W Model : M32 Sequence Code : 000000000000E3206 HiperDispatch : NO
CPC Capacity : 2780 Change Reason : NONE

CPU Number	CPU Type	Time% Online	Time% LPAR Busy	Time% MVS Busy	Time% Parked	LOG PROC Share%	HiperDispatch Priority	I/O Interrupts Rate	I/O Interrupts% via TPI
0	CP	100.00	1.60	1.57	-----	31.9		1.87	0.18
1	CP	100.00	1.14	1.12	-----	31.9		2.69	0.33
2	CP	100.00	0.85	0.83	-----	31.9		2.72	0.29
TOTAL/AVERAGE			1.20	1.18		95.7		7.27	0.28

- There are two possible reasons for an I/O interrupt delay:
 - The LPAR is not dispatched
 - There are not enough CPs that are enabled to handle interrupts
- I/O interrupt delay time is NOT included in the total I/O response time as reported by RMF
- In the past I/O interrupt delay time could not even been measured.
- When data transfer is complete on an I/O device, the channel subsystem will attempt to find a CP (idle or busy) that is enabled for interrupts
- After the CP completes processing for an I/O interrupt, it issues a Test Pending Interrupt (TPI) instruction to determine whether there are any further I/O interrupts pending. If yes, the processor proceeds to service that interrupt
- Hence, an interrupt handled via TPI is a **queued** interrupt, that could not be handled instantly by an alternate I/O enabled processor
- Not more than 20-30% should be handled via TPI, otherwise it is time to examine the I/O interrupt delay time

zEC12 – I/O Interrupt Delay Time

- ▶ New field AVG INT DLY in RMF Postprocessor Device Activity report.
- ▶ Caution: Interrupt Delay Time is not included in AVG RESP Time



D I R E C T A C C E S S D E V I C E A C T I V I T Y															
z/OS V1R13				SYSTEM ID TRX2				DATE 11/23/2011				INTERVAL 14.59.998			
				RPT VERSION V1R13 RMF				TIME 12.30.00				CYCLE 1.000 SECONDS			
TOTAL SAMPLES =		900		IODF = 01		CR-DATE: 11/15/2011		CR-TIME: 07.33.54		ACT: POR					
								DEVICE	AVG	AVG	AVG	AVG	AVG	AVG	AVG
STORAGE	DEV	DEVICE	NUMBER	VOLUME	PAV	LCU	ACTIVITY	RESP	IOSQ	CMR	DB	INT	PEND	DISC	CONN
GROUP	NUM	TYPE	OF CYL	SERIAL			RATE	TIME	TIME	DLY	DLY	DLY	TIME	TIME	TIME
XTEST	2208	33903	3339	TRXSX9	1	0032	0.001	.384	.000	.128	.000	.123	.256	.000	.128
XTEST	2209	33903	3339	TRXSXA	1	0032	0.001	.256	.000	.000	.000	.135	.256	.000	.000
	220A	33909	10017	TRXT01	1	0032	0.000	.000	.000	.000	.000	.000	.000	.000	.000
	220B	33909	10017	TRXT02	1	0032	0.000	.000	.000	.000	.000	.000	.000	.000	.000

- z/OS V1.12 and V1.13 RMF is extended to report the interrupt delay time measurement for devices attached to the IBM zEnterprise EC12 server.
- Support available with new function APAR OA39993
- New Interrupt Delay Time reported in RMF Postprocessor Device Activity report:

AVG INT DLY: The average interrupt delay time in units of milliseconds encountered for I/O requests to this device.
For each I/O request, the time is measured from when the I/O operation is complete to when the operating system begins to process the status.

zEC12 – Enhanced CF Link Reporting

- ▶ In a System z environment different types of coupling links can be used to connect a Coupling Facility (CF) to the operating system.
- ▶ Each coupling link type has effect on link performance, response times and coupling overheads.
- ▶ For configurations covering large distances, the time spent on the link can be the largest part of the response time.



Type	Description	CHPID Type	Link Rate	Distance
ISC-3	InterSystem Channel-3	CFP (CF Peer)	2 Gbps	10 km unrepeated (6.2 miles) 100 km repeated
PSIFB	12x IB-DDR Parallel Sysplex InfiniBand	CIB (Coupling over Infiniband)	6 GBps	150 meters (492 feet)
	12x IB-SDR Parallel Sysplex InfiniBand		3 GBps (When connected to a System z9 EC or System z9 BC)	
PSIFB-LR	1x IB-SDR Parallel Sysplex InfiniBand – Long Reach Double data rate (1 x IB-DDR) is supported if connected to a System z qualified DWDM supporting DDR.	CIB (Coupling over Infiniband)	2.5 Gbps 5.0 Gbps	10 km unrepeated (6.2 miles) 100 km repeated
IC	Internal Coupling Channel	ICP (Internal CF Peer)	Internal speeds	n/a

- With system z, different types of coupling links can be used to connect a Coupling Facility (CF) to an operating system. Each coupling link type has effect on link performance, response times and coupling overheads.
- For configurations covering large distances, the time spent on the link can be the largest part of the response time. The table gives an overview of the current types of coupling links supported by system z.
- With new function APAR OA37826 the Postprocessor Coupling Facility Activity report and Monitor III CFSYS report are enhanced to display additional channel path information for channel paths of type CIB or CFP.
- The RMF support is available for z/OS V1.12 and V1.13 RMF

zEC12 – Enhanced CF Link Reporting



RMF Postprocessor Coupling Facility Activity Report:

⇒ New CHANNEL PATH DETAILS in Subchannel Activity Section

System Name	CF Link ID	CF Link Type	Operation Mode	Degraded	Distance	PCHID	Host Channel Adapter ID	Host Channel Adapter Port Number	I/O Processor IDs
TRX1	F8	CFP	2Gbit		0	271			03
TRX1	E2	CIB	12x IFB HCA2-O	N	<1	700	001C	01	05
TRX1	E8	ICP							
TRX1	E5	CIB	12x IFB3 HCA3-O	N	<1	703	000B	02	0B
TRX1	E3	CIB	12x IFB HCA2-O	N	<1	701	001C	02	05
TRX1	E9	ICP							
TRX1	E4	CIB	12x IFB3 HCA3-O	N	<1	702	000B	01	0B

▶ **CF to CF Activity for Coupling Facility CF01**

▶ **Usage Summary for Coupling Facility CF02**

- New function APAR OA37826 adds a new CHANNEL PATH DETAILS section to the Subchannel Activity and CF To CF Activity sections of the RMF Postprocessor Coupling Facility Activity report.
- The enhanced subchannel reporting function is provided by the zEnterprise EC12 (zEC12) processor for CF link types CIB or CFP and require the following prerequisites:
 - To report or display the additional channel path information for directly-connected CFs, z/OS must be running on a zEC12 processor.
 - To report or display the additional channel path information for remotely-connected CFs, the directly-connected CF must be running on a zEC12 processor (CFLEVEL 18 or higher).
- For a full exploitation of this new support in a sysplex environment it is necessary to install this APAR on all systems of the sysplex.

OPERATION MODE: Channel path operation mode. It describes the data rate, bandwidth, protocol and adapter type of the channel path.

Data rates for CFP channels paths:

- 1GBIT - 1.0625 Gbit/sec
- 2GBIT - 2.125 Gbit/sec

Bandwidth for CIB channels paths:

- 1x - single bandwidth
- 12x - twelve-fold bandwidth

Protocol for CIB channels paths:

- IFB or IFB3

Adapter types for CIB channels paths:

- HCA-O, HCA-O LR, HCA3-O or HCA3-O LR

Unknown operation mode:

- UNKNOWN

zEC12 – Enhanced CF Link Reporting...



RMF Postprocessor Coupling Facility Activity Report:

⇒ New CHANNEL PATH DETAILS in CF to CF Activity Section

COUPLING FACILITY NAME = X5CFP87											
CF TO CF ACTIVITY											
PEER CF	# REQ TOTAL AVG/SEC	-- CF LINKS -- TYPE	USE		REQUESTS # REQ	-SERVICE AVG	TIME(MIC) STD_DEV		# REQ		
X5CFH89	243089 270.1	CFP	2	SYNC	243089	18.6	4.9	SYNC	0	0.0	0.0
X5CFR89	34647K 38497	CIB	6	SYNC	34647K	12.4	4.0	SYNC	83	8.4	9.0
CHANNEL PATH DETAILS											
PEER CF	ID	TYPE	OPERATION MODE			DEGRADED	DISTANCE				
X5CFH89	02	CFP	2GBIT				0				
	03	CFP	2GBIT				0				
X5CFR89	D0	CIB	12X	IFB	HCA3-0	N	<1				
	D1	CIB	12X	IFB	HCA3-0	N	<1				
	D2	CIB	12X	IFB	HCA3-0	N	<1				
	D3	CIB	12X	IFB	HCA3-0	N	<1				
	E0	CIB	12X	IFB3	HCA3-0	Y	<1				
	E1	CIB	12X	IFB3	HCA3-0	Y	<1				

Channel path details for CF to CF links of type CIB or CFP:

- Operation mode
- Degraded status
- Link distance

DEGRADED: Character **Y** in this column indicates that the channel path is operating at reduced capacity (degraded) or not operating at all.

DISTANCE: Estimated distance in kilometer. The value is calculated as follows:

Average round-trip path time in microseconds

10 microseconds / kilometer

The value '<1' means that the estimated distance is below one kilometer.
A value of zero means that the time was not measured.

PCHID: Physical channel ID.

HCA ID: The hexadecimal host channel adapter ID.

HCA PORT: The hexadecimal host channel adapter port number.

IOP IDS: The hexadecimal identifiers of I/O processors (System Assist Processors) to which the channel path is accessible.

zEC12 – Enhanced CF Link Reporting...

RMF Monitor III CFSYS Report:
Channel Paths Details Pop-up

RMF Coupling Facility - Subchannels and Paths

Press Enter to return to the Report panel.

Details for System : TRX1
Coupling Facility : CF01

Subchannels Generated : 149
In Use : 49
Max : 49

Channel Path Details:

ID	Type	Operation Mode	Deg	Distance	PCHID	---HCA---	ID	Port	--IOP IDs--
E2	CIB	12x IFB HCA2-O	N	<1	0700	001C	01	05	
E3	CIB	12x IFB HCA2-O	N	<1	0701	001C	02	05	
E4	CIB	12x IFB3 HCA3-O	N	<1	0702	000B	01	0B	
E5	CIB	12x IFB3 HCA3-O	N	<1	0703	000B	02	0B	
E8	ICP								
E9	ICP								
F8	CFP	2Gbit		0	0271			03	

Scrollable List
of all available Channel Paths
to Coupling Facility

- The 'Subchannels and Paths' pop-up panel of the RMF Monitor III Coupling Facility Systems Report (CFSYS) report is modified to show a scrollable list of all channel paths that are available to the reported coupling facility.

zEC12 - Support of Crypto Express4 Card



CRYPTO HARDWARE ACTIVITY

z/OS V1R13

SYSTEM ID SYSF
RPT VERSION V1R13 RMF

DATE 11/29/2011
TIME 16.00.00

All measurements
available for
Crypto Express4 Card

CRYPTOGRAPHIC COPROCESSOR					
----- TOTAL -----					
TYPE	ID	RATE	EXEC TIME	UTIL%	KEY-GEN RATE
CEX2C	0	0.00	0.000	0.0	0.00
	1	2.16	295.9	63.9	2.14
CEX3C	2	0.00	0.000	0.0	0.00
CEX4C	4	2.15	227.8	48.9	2.15

CRYPTOGRAPHIC ACCELERATOR						ME-FORMAT RSA OPERATIONS			CRT-FORMAT RSA OPERATIONS		
----- TOTAL -----						--			--		
TYPE	ID	RATE	EXEC TIME	UTIL%	KEY	RATE	EXEC TIME	UTIL%	RATE	EXEC TIME	UTIL%
CEX2A	3	766.9	0.434	33.3	1024	362.4	0.521	18.9	369.5	0.183	6.8
					2048	0.00	0.000	0.0	34.99	2.175	7.6
CEX4A	5	998.9	0.365	36.5	1024	246.4	0.534	13.2	554.3	0.205	11.3
					2048	0.00	0.000	0.0	83.16	0.689	5.7
					4096	0.00	0.000	0.0	115.1	0.547	6.3

ICSF SERVICES											
ENCIPHERMENT				DECIPHERMENT			MAC		HASH		PIN
RATE	SDS	TDES	AES	SDS	TDES	AES	GENERATE	VERIFY	SHA-256	SHA-512	TRANSLATE
0.00	0.00	0.00	0.00	0.00	0.00	0.00	0.00	0.00	0.00	0.00	0.00
SIZE	0.00	0.00	0.00	0.00	0.00	0.00	0.00	0.00	0.00	0.00	0.00

- RMF new function APAR OA37016 introduces the RMF support of the Crypto Express4S feature on the zEC12
- In detail, RMF collects and reports performance measurements for operations executed on Crypto Express4S co-processors (CEX4C) and accelerators (CEX4A).
- CEX4C measurements are stored in the Cryptographic Coprocessor data section and CEX4A measurements are stored in the Cryptographic Accelerator data section of SMF record 70 subtype 2.
- The Postprocessor Crypto Activity report provides CEX4C measurements in the CRYPTOGRAPHIC COPROCESSOR section and CEX4A measurements in the CRYPTOGRAPHIC ACCELERATOR section.
- The RMF support is available for z/OS V1.10 and above

zEC12 - Warning Track Interruption Facility Statistics



- ▶ In a PR/SM™ environment the LPAR hypervisor assigns physical engines to logical engines accordingly to the weighting factors of the partitions.
- ▶ Once the time slice for a logical engine is expired the currently executing work is suspended until a physical engine is assigned to the logical engine again.
- ▶ The Warning Track Interruption Facility notifies the operating system that PR/SM™ will undispach a certain logical processor within the next 50 microseconds (grace period).
- ▶ z/OS is now able to save status for the running unit of work and re-dispatch the work unit on a different logical processor within the grace period.
- ▶ z/OS now signals to PR/SM that the logical processor can be undispached.
- ▶ Warning Track processing is only supported in HyperDispatch=YES environments.
- ▶ A high benefit can be achieved for Vertical Medium and Low (VM/VL) processors that have a smaller capacity share guaranteed by PR/SM



zEC12 - Warning Track Interruption Facility Statistics...



- ▶ RMF keeps track of the number of times PR/SM issued a warning-track interruption to a logical processor and z/OS was able/unable to return the logical processor within the grace period.
- ▶ RMF measures the amount of time in microseconds that a processor was yielded to PR/SM due to Warning-track processing.

SMF record type 70 subtype 1 (CPU Activity) – CPU data section				
Offset	Name	Length	Format	Description
80 x50	SMF70WTS	4	Binary	The number of times PR/SM issued a warning-track interruption to a logical processor and z/OS was able to return the logical processor within the grace period.
84 x54	SMF70WTU	4	Binary	The number of times PR/SM issued a warning-track interruption to a logical processor and z/OS was unable to return the logical processor within the grace period.
88 x58	SMF70WTI	4	Binary	Amount of time in microseconds that a logical processor was yielded to PR/SM due to Warning Track processing.



RMF Postprocessor Overview Conditions		
Name	Qualifier	Description
WTRKCP (WTRKAAP) (WTRKIIP)	cpu-id	The percentage of times PR/SM issued a warning-track interruption to a processor and z/OS was able to return it to PR/SM within the grace period.
WTRKTCP (WTRKTAAP) (WTRKTIIP)	cpu-id	Time in microseconds that a purpose processor was yielded to PR/SM due to Warning Track processing.



30

- With new function APAR OA37803 RMF supports the Warning-Track-Interruption-Facility on zEC12.
- The CPU Data Section of SMF Record 70 Subtype 1 is enhanced with new warning track statistics.
- A set of new Overview/Exception Conditions can be used to report the new measurements.
- The RMF support is available for z/OS V1.12 and V1.13 RMF.

RMF Monitor III zIIP Exploitation

- ▶ With z/OS V2R1 RMF, the Monitor III Data Gatherer (RMFGAT) can partially offload work to zIIP processors
- ▶ By default the RMF Monitor III Data Gatherer (RMFGAT) is enabled for zIIP exploitation
- ▶ When at least one zIIP processor is online for an LPAR, RMFGAT is partially offloading work to this processor without any further user interaction
- ▶ The RMFGAT zIIP exploitation can be controlled initially by means of the new Monitor III parmlib option ZIIPUSE

```
SYNC(00)          /* MINTIME SYNCHRONIZATION          */  
SYSOUT(A)         /* MESSAGES TO SYSOUT CLASS A      */  
WSTOR(32)         /* SIZE OF INSTORAGE BUFFER (IN MB) */  
ZIIPUSE           /* PARTIAL USE OF ZIIP ENGINES     */  
IOSUB            /* I/O SUBSYSTEM GATHERING ACTIVE  */  
CFDETAIL          /* COUPLING FACILITY DETAILS       */  
CACHE             /* ACTIVATE CACHE GATHERING        */  
VSAMRLS          /* ACTIVATE VSAM RLS GATHERING     */  
OPD              /* ACTIVATE OMVS PROCESS DATA GATHERING */
```


New Option
ZIIPUSE

- ▶ The RMFGAT zIIP exploitation can be activated/deactivated dynamically by means of the following command: F RMF,F III,ZIIPUSE/NOZIIPUSE

- The RMF Monitor III data gatherer (RMFGAT) has been entitled to partially run on IBM System z Integrated Information Processors (zIIPs).
- A new Monitor III gatherer option ZIIPUSE/NOZIIPUSE is introduced to determine whether the RMFGAT address space is eligible for zIIP exploitation.

RMF Monitor III zIIP Exploitation...

- ▶ When at least one zIIP processor is recognized by the Monitor III gatherer, RMFGAT will schedule an Enclave SRB and offloads the Coupling Facility gathering to the zIIP processor



```

Session C - [32 x 80]
File Edit View Communication Actions Window Help
Host: tn3270.de.ibm.com Port: 23 LU Name: Disconnect
RMF V2R1 Enclave Report Line 1 of 2
Command ==> _ Scroll ==> CSR

RMF Enclave Details
Details for enclave ENC00001 with token 00000034 00000006
Press Enter to return to the Report panel.

- CPU Time - - - - - zAAP Time - - - - - zIIP Time -
Total 1327 Total 0.000 Total 1327
Delta 1.067 Delta 0.000 Delta 1.067

*S EN State ---- Using ---- Delay ----- IDL UNK
Samples CPU AAP IIP I/O CPU AAP IIP I/O STO CAP QUE
120 0.0 0.0 0.0 0.0 0.0 0.0 0.0 0.0 0.0 0.0 0.0 0.0 0.0 100
    
```


- ▶ In case the zIIP processor is activated dynamically by the CONFIG CPU(xx),ONLINE command, RMFGAT can exploit this processor starting with the next MINTIME
- ▶ Installations without Coupling Facilities (e.g. Monoplex) won't see significant RMFGAT zIIP activity

- When at least one zIIP processor is recognized by the Monitor III gatherer, RMFGAT will schedule an Enclave SRB and offloads the RMF Coupling Facility data gathering to the zIIP processor.
- The Enclave will be displayed in RMF Monitor III Enclave report. In the Enclave Details pop-up panel you will see the RMFGAT CPU time offloaded to zIIP.
- If the zIIP will be taken online dynamically, it will be recognized by RMFGAT and the zIIP will be exploited with the start of the next Monitor III Mintime.
- When no zIIPs are online, RMFGAT will neither create an enclave nor schedule any zIIP eligible SRB work. That means, no zIIP time on CP will appear in any performance reports.
- Since RMFGAT only offloads the Coupling Facility data gathering, installations without Coupling Facilities will not benefit from the zIIP exploitation.

Postprocessor XML Formatted Reports

Rationale:

- ▶ RMF Postprocessor reports are limited to a page width of 132 characters
- ▶ No state-of-the-art display capability of Postprocessor reports
- ▶ No easy access to RMF Postprocessor data for application programs
 - ⇒ cumbersome to parse the text output
 - ⇒ each report has its own layout



RMF Postprocessor reports can now be generated in XML Format

In the past, users of the RMF Postprocessor had to struggle with a couple of shortcomings:

- The standard text output was limited to a width of 132 characters. Therefore some reports appeared somehow squeezed. This applies in particular to Overview Reports with a high number of OVW conditions
- The basic text format didn't exploit today's presentation capabilities like resizing windows, scrolling back and forth etc.
- Depending on the report type, the report layouts were quite different. Hence, API programs need to supply specific logic in order to extract metrics out of the reports

Starting with z/OS V1R11 RMF, the Postprocessor is able to generate a subset of the reports alternatively in XML format.

Postprocessor XML Formatted Reports...



z/OS V1R11 RMF	z/OS V1R12 RMF	z/OS V1R13 RMF	z/OS V2R1 RMF
CPU Activity CRYPTO Activity FICON Director Activity ESS Disk Systems Activity OMVS Kernel Activity report OVERVIEW Report	DEVICE Activity WORKLOAD Activity	PAGING Activity SDELAY (XML only)	CACHE Subsystem Activity CF Activity CHANNEL Path Activity ENQUEUE Activity HFS Statistics IOQ Activity PCIE Activity (XML-only) PAGESP Activity SDEVICE Activity report VSTOR Activity XCF Activity

- ▶ Summary and Exception reports as well as interval reports based on data collected by a Monitor II background session are not available in XML format
- ▶ The XML format is the preferred RMF Postprocessor Report format for the future
- ▶ The XML Format supersedes the Text format. New Reports might not be implemented in Text format



34 Complete your session evaluations online at www.SHARE.org/Pittsburgh-Eval

- It was RMF's objective to introduce the XML format for the majority of Postprocessor reports during the past releases. This work is now completed with RMF for z/OS V2.1.
- With the first stage in RMF for z/OS 1.11, those reports have been selected where no similar Monitor III report is available – since Monitor III reports are already XML enabled by means of the Data Portal. These are the following Postprocessor single-system reports:
 - CPU Activity report
 - CRYPTO Hardware Activity report
 - FICON Director Activity report
 - OMVS Kernel Activity report,
 - ESS Disk Systems Activity report
- In addition, Postprocessor Overview reports belong also to the first stage since multiple Overview conditions have caused nasty line-feeds in the old text format.
- RMF for z/OS 1.12 extends the list of Postprocessor XML reports with another single- system report and the first sysplex report:
 - DEVICE Activity report (single-system report)
 - WLMGL Workload Activity report (sysplex report)
- z/OS 1.13 added the PAGING Activity report and the Serialization Delay report (SDELAY) which was the first report that is only available in XML format. Now with z/OS 2.1, the list of available reports is completed with:
 - CACHE Subsystem Activity report
 - CF Coupling Facility Activity report
 - CHANNEL Path Activity report
 - ENQueue Activity report
 - HFS Hierarchical File System report
 - IOQ I/O Queuing Activity report
 - PCIE Activity Report
 - PAGESP Page Data Set Activity report
 - SDEVICE Shared Device Activity report
 - VSTOR Virtual Storage Activity report
 - XCF Cross-System Coupling Activity report

Postprocessor XML Formatted Reports...


- ▶ The generation of Postprocessor reports in XML format is controlled by the new ddnames XPRPTS, XPXSRPTS and XPOVWRPT
- ▶ If the XML output is routed to permanent data sets rather than to SYSOUT, define the data set with RECFM=VB and LRECL between 256 and 8192. Specify an appropriate BLKSIZE.

ddname	Contents	Allocations	Notes
XPRPTS	Combined single-system report in XML format	One ddname for one data set to contain all single system reports for each interval during the session.	There is no dynamic allocation of this ddname, you have to define it explicitly if you want to get all reports in XML format into one data set or output class. If you define this ddname, no MFRnnnnn files are created. If you define this ddname and PPRPTS, no XML output in file XPRPTS is created.
XPOVWRPT	Combined Overview report in XML format	One ddname for one data set to contain all overview reports for each system included in the input data.	There is no dynamic allocation of this ddname, you have to define it explicitly if you want to get all overview reports in XML format into one data set or output class. If you define this ddname, no PPORPnnn files are created.
XPXSRPTS	Combined sysplex-wide report in XML format	One ddname for one data set to contain all sysplex reports for each interval included in the input data.	There is no dynamic allocation of this ddname, you have to define it explicitly if you want to get all reports in XML format into one data set or output class. If you define this ddname, no MFRnnnnn files are created. If you define this ddname and PPXSRPTS, no XML output in file XPXSRPTS is created.

- The request for XML output from the RMF Postprocessor is triggered by means of the existence of a DD card for XPRPTS (for single-system reports) , XPOVWRPT (for Overview reports) and/or XPXSRPTS (for sysplex-wide reports) in the JCL for the Postprocessor job.
- If one of these DD statements are defined in the JCL, then XML output will be generated.
- The following rules apply, if requests for text and XML are given simultaneously:
 - If the user specifies a DD card for cumulative text output, i.e. PPRPTS, as well as XPRPTS, then only text output will be generated into PPRPTS and no XML is produced.
 - If the user specifies the PPXSRPTS ddname for cumulative text output together with XPXSRPTS, no XML output is generated.
 - If single-system reports are requested on the REPORTS control statement which are not XML enabled and the DD card XPRPTS is defined, no output is generated for them.


HTTP API to access Postprocessor XML Reports

- ▶ Web browser can be used as Postprocessor Data Portal
- ▶ All RMF Postprocessor XML formatted reports supported
- ▶ Application programs can use Distributed Data Server (DDS) HTTP API to retrieve RMF Postprocessor XML reports



- In most installations, the access to historical data is needed for in depth performance analysis. This allows to keep track whether a critical situation has been persistent or not.
- The existing HTTP API of the RMF Distributed Data Server (DDS) already provides a sysplex-wide access of the data collected by RMF Monitor III. With RMF for z/OS 1.12 this API is extended by the capability to grant instant and easy access to RMF long-term historical data as reported by the RMF Postprocessor.
- Application programs can exploit the extended DDS HTTP API by sending standard URL requests for historical RMF Postprocessor data to the DDS.
- Since DDS returns the requested data as XML document, a web browser can act as an RMF Postprocessor Data Portal to access historical RMF data which is generated by the RMF Postprocessor in XML format.

HTTP API to access Historical Data...



37 Complete your session evaluations online at www.SHARE.org/Pittsburgh-Eval

- To get access to RMF Postprocessor data provided by the DDS, the GPMSSERVE started task is extended with an additional DD card:

```
//GPMPJCL DD DISP=SHR,DSN=SYS1.SERBPWSV(GPMPJCL)
```
- This DD statement points to a JCL template which contains all JCL statements necessary to start a Postprocessor job from the RMF Distributed Data Server. The JCL template is stored in SYS1.SERBPWSV(GPMPJCL).
- You must adapt or replace the GPMPJCL member to suit your installation, ensuring that the DDS is able to run RMF Postprocessor jobs. If you do not want to request Postprocessor data with the DDS, you can omit the GPMPJCL ddname.
- The dataset or the member specified in the GPMPJCL DD card can be replaced with private ones containing the JCL template for running RMF Postprocessor from the DDS.
- The JCL template that is used by DDS to start the Postprocessor JOB does not contain any Postprocessor control statements. These will be dynamically created by DDS depending on the HTTP request parameters.
- For a detailed description of the DDS HTTP API please refer to the *z/OS RMF Programmer's Guide*.

Notes:

- The Postprocessor API functionality is only available with JES2 installed.
- The DD card specifications for the XML output datasets must not be changed. To be able to retrieve the Postprocessor output, DDS needs these SYSOUT data sets to reside on spool.

Postprocessor XML Formatted Reports...



RMF Data Portal for z/OS

Welcome, you are connected to: ,SYSDPLEX,SYSPLEX

RMF Monitor III Data:

Icon	Resource	Metrics	Attributes
	,SYSDPLEX,SYSPLEX	Metrics	Show

RMF Postprocessor Reports:

Reports:

☐ CACHE ☐ CHAN ☐ CPU ☐ CRYPTO ☐ DEVICE ☐ ENQ ☐ ESS ☐ FCD ☐ HFS ☐ IOQ ☐ OMVS ☐ PAGESP ☐ PAGING ☐ PCIE ☐ SDELAY ☐ VSTOR ☐ XCF
☐ CF ☐ SDEVICE ☒ WLMGL
☐ OWW

Filter Options:

Date(Start,End) 20130927,20130927 POLICY
 SysID RCLASS
 Time of Day 0800,1600 RCPER
 Duration 0100 SCLASS BATCHHI
 SCPER
 SYSNAM
 WGPOR
 WGROUP

38 Complete your session evaluations online at www.SHARE.org/Pittsburgh-Eval

The RMF Data Portal for z/OS allows to generate and display and RMF Postprocessor XML report:

- When you click the *Explore* button on the welcome screen, the Data Portal displays a list of Postprocessor XML enabled reports.
- The selection of a Postprocessor report triggers an HTTP request that will retrieve, format and display the Postprocessor report in the web browser

With RMF for z/OS 2.1 the GUI of the RMF Data Portal for z/OS was enhanced:

- For each Postprocessor report type you can now specify additional options that will be used as Postprocessor report control statements.
- These options allow to filter the generated Postprocessor XML report, so that the amount of XML output can be reduced.
- This helps to improve the performance to generate and display a Postprocessor XML report in the RMF Data Portal for z/OS.

Postprocessor XML Formatted Reports...



RMF Data Portal for z/OS

Display Controls for RMF Postprocessor Report

Report Data Selection:

- 09/27/2013-04:29:35 SYSE CPU
- 09/27/2013-04:29:35 S4 CPU
- 09/27/2013-04:44:35 SYSE CPU
- 09/27/2013-04:44:35 S4 CPU

Show all Report Data

RMF Postprocessor Interval Report [System SYSE] : CPU Activity Report

RMF Version : z/OS V2R1 SMF Data : z/OS V2R1
 Start : 09/27/2013-04:29:35 End : 09/27/2013-04:44:35 Interval : 14:59:999 minutes Cycle : 1000 milliseconds

CPU Activity

CPU : 2827 Model : 741 HW Model : H43 Sequence Code : 0000000000004255 HiperDispatch : YES CPC Capacity : 4499 Change Reason : NONE

CPU Number	CPU Type	Time% Online	Time% LPAR Busy	Time% MVS Busy	Time% Parked	LOG PROC Share%	HiperDispatch Priority	I/O Interrupts Rate	I/O Interrupts% via TPI
0	CP	100.00	1.88	1.86	0.00	50.1	MED	4.27	0.42
1	CP	100.00	0.86	0.84	0.00	50.1	MED	3.16	0.74
2	CP	100.00	0.00	-----	100.00	0.0	LOW	0.00	0.00
TOTAL/AVERAGE CP			0.91	1.35		100.2		7.42	0.55

System Address Space Analysis

Type	Number of Address Spaces: MIN	Number of Address Spaces: MAX	Number of Address Spaces: AVG
IN Queue	59	60	59.2
IN READY Queue	0	1	0.0
OUT READY Queue	0	0	0.0
OUT WAIT Queue	0	0	0.0
LOGICAL OUT READY Queue	0	0	0.0

39 Complete your session evaluations online at www.SHARE.org/Pittsburgh-Eval

The new stylesheets and JAVA script code, used to format and display the Postprocessor XML report in the web browser introduces new functionality that helps to analyse the RMF performance data:

- You can now select a single report interval or a set of report intervals to focus on the RMF performance data for specific report interval(s).
- You can expand/collapse report section(s) so that it's easier to get an overview about the reported data.

Postprocessor XML Formatted Reports...



The RMF Data Portal is currently limited to the SMF Buffer of the RMF Sysplex Data Server.
No SMF Dump Data Sets can be specified

```
//SHARAnnX JOB (DE03141,,),'SHARAnn',CLASS=A,USER=SHARAnn,
//          MSGCLASS=H,MSGLEVEL=(1,1),NOTIFY=SHARAnn
//*
//XMLPP    PROC REPORT=
//RMFPP    EXEC PGM=ERBRMFPP,COND=(4,LT,GETSMF)
//MFPINPUT DD DISP=(OLD,PASS),DSN=*.RMFSORT.SORTOUT
//MFPMSGDS DD SYSOUT=*
//XPRPTS   DD PATH='/sharelab/sharann/xmlpp/&REPORT..xml',
//          PATHOPTS=(OWRONLY,OCREAT,OTRUNC),
//          PATHMODE=(SIRUSR,SIWUSR,SIRGRP),FILEDATA=TEXT
//XPSRPTS   DD PATH='/sharelab/sharann/xmlpp/&REPORT..xml',
//          PATHOPTS=(OWRONLY,OCREAT,OTRUNC),
//          PATHMODE=(SIRUSR,SIWUSR,SIRGRP),FILEDATA=TEXT
//          PEND
//PPCPU    EXEC PROC=XMLPP,REPORT=CPU
//RMFPP.SYSIN DD *
//          REPORTS(CPU)
//PPWLMGL  EXEC PROC=XMLPP,REPORT=WLMGL
//RMFPP.SYSIN DD *
//          SYSRPTS(WLMGL(SCPER,POLICY))
//
```


Execute the Postprocessor JCL
and redirect the output to any
HFS directory

- The RMF Postprocessor report generation via the RMF Data Portal for z/OS is currently limited to the SMF records in the SMF Buffer of the RMF Sysplex Data Server since no SMF Dump Data Sets can be specified in the HTTP request for the Postprocessor API.
- However, you can use an RMF Postprocessor JOB to generate an XML report from any SMF source and redirect the XML output to a permanent file in the USS filesystem.
- Now that you have generated a report, there are multiple ways to view the XML output:
 - Transfer the XML file in ASCII mode to your windows workstation and use the RMF Postprocessor XML Toolkit to display the report in your web browser as an HTML document.
 - Or, if you don't want to transfer the XML report to your workstation, you can think about using an SMB Server to map the USS directory tree to a network drive or you can setup an HTTP server that runs on z/OS and allows to view the XML reports in the USS directory.

Postprocessor XML Report Access via IBM HTTP Server



RMF Postprocessor Reports:
Everywhere and Anytime



- ✓ Instant Access to all Reports
- ✓ No Maintenance of raw Data Archives

- Since the reports are pure XML, an arbitrary web browser is perfectly suited to display the reports in a state-of-the art fashion.
- Once you have created a USS directory with XML reports by means of a Postprocessor job, you can use the IBM HTTP Server instantly as gateway.
- The reports can remain in the USS directory of your z/OS system and you can forget about cumbersome downloads.
- Once the HTTP server setup is done by means of a few entries in the servers configuration file (httpd.conf), you can easily navigate within the USS directory structure.
- If you select the report of your choice, it will be displayed instantly in the browser window.

RMF XP Enhancements


- ▶ RMF **XP** is the solution for **C**ross **P**latform Performance Monitoring
- ▶ RMF **XP** supports the Operating Systems running on
 - ⇒ **x** Blades
 - ⇒ **p** Blades



- ▶ In addition RMF XP supports Linux on System z
 - ⇒ LPAR Mode
 - ⇒ VM Guest Mode

- RMF XP is the new solution to monitor the performance of heterogeneous environments. RMF XP supports the operating systems running on the IBM zEnterprise BladeCenter Extension:
 - AIX on System p
 - Linux on System x
 - Windows on System x (New with z/OS 2.1)
- In addition, Linux on System z is supported as well

RMF XP – Component Overview



43 Complete your session evaluations online at www.SHARE.org/Pittsburgh-Eval

- The core component of RMF XP is the GPM4CIM started task.
- Similar to the existing Distributed Data Server for z/OS (aka GPMSEVERE) the GPM4CIM started task can receive HTTP requests and sends back responses in terms of structured XML documents.
- Since the GPM4CIM started task runs in the z/OS Unix System Services (USS) environment, at least one z/OS system is needed to utilize the RMF XP component.
- With z/OS V2R1, RMF XP uses the CIM client API to collect performance data from Windows systems in the same way it is used for AIX or Linux systems.


ISD Platform Agent for Windows

Components on the Windows Endpoints:

- ✓ CIM Server (Pegasus Port for Windows)
- ✓ CIM Provider
- ✓ Performance Data Collector

All Components are included
in the IBM Systems Director
Platform Agent for Windows

- ▶ The Package can be downloaded as installable image from the following URL:
<http://www.ibm.com/systems/software/director/downloads/agents.html>
- ▶ When the installation is complete, check if the following services have been started:



IBM CIM Listener Service	CIM Listene...	Started
IBM Command Line Trace	Enables co...	
IBM Platform Agent Watchdog Service	Watchdog S...	Started
IBM SLP Attributes Service	SLP Attribut...	Started
IBM SLP SA	IBM SLP Ser...	Started
IBM Standard Asset Manager Service		Started
IBM Windows Gatherer Service		Started
IBM Windows Repository Service		Started
IBM WMI+ A Service	WMI CIM S...	Started

44 Complete your session evaluations online at www.SHARE.org/Pittsburgh-Eval

- The RMF XP support for the Windows operating system requires the following components on the windows endpoints:
 - CIM Server (The Open Pegasus CIM server)
 - CIM Provider
 - Performance Data Collector
- These components are included in the IBM Systems Director (ISD) Platform Agent for Windows. You will find more information about the ISD Platform Agent for Windows in the publications for „IBM Systems Director v6.3.2“
- A no-charge version of the ISD agent is available from the following website:
<http://www.ibm.com/systems/software/director/downloads/agents.html>

RMF XP Windows Support – Invocation



- ▶ Started Task: SYS1.PROCLIB(GPM4CIM)
- ▶ Runs in USS Environment via BPXBATCH
- ▶ Multiple instances can run in parallel: one STC per platform
 - ▶ S GPM4CIM.GPM4A,OS=A
 - ▶ S GPM4CIM.GPM4X,OS=X
 - ▶ S GPM4CIM.GPM4Z,OS=Z
 - ▶ **S GPM4CIM.GPM4W,OS=W**


```
//GPM4CIM PROC OS=W
//STEP1 EXEC PGM=BPXBATCH,TIME=NOLIMIT,REGION=0M,
// PARM='PGM /usr/lpp/gpm/bin/gpm4cim cfg=/etc/gpm/gpm4&OS..cfg'
//STDENV DD PATH='/etc/gpm/gpm4cim.env'
//STDOUT DD PATH='/var/gpm/logs/gpm4cim&OS..out',
// PATHOPTS=(OWRONLY,OCREAT,OTRUNC),
// PATHMODE=(SIRUSR,SIWUSR,SIRGRP)
//STDERR DD PATH='/var/gpm/logs/gpm4cim&OS..trc',
// PATHOPTS=(OWRONLY,OCREAT,OTRUNC),
// PATHMODE=(SIRUSR,SIWUSR,SIRGRP)
//SYSPRINT DD SYSOUT=*
//SYSOUT DD SYSOUT=*
// PEND
```



- To start the GPM4CIM server, RMF provides procedure GPM4CIM as a member in SYS1.PROCLIB, which you can modify according to your needs.
- The cfg parameter in the PARM statement points to the GPM4CIM configuration file.
- Since one instance of GPM4CIM is needed per platform, no unique configuration file is used. Hence, different configuration files are supplied by means of the OS variable which denotes the following target platforms:
 - A AIX on system p
 - X Linux on system x
 - Z Linux on system z
 - W Windows on system x

RMF XP Windows Support – Configuration


```
//GPM4CIM PROC OS=A
//STEP1 EXEC PGM=BPXBATCH,TIME=NOLIMIT,REGION=0M,
// PARM='PGM /usr/lpp/gpm/bin/gpm4cim cfg=/etc/gpm/gpm4cim.cfg'
//STDENV DD PATH='/etc/gpm/gpm4cim.env'
//STDOUT DD PATH='/var/gpm/logs/gpm4cim&OS..out',
// PATHOPTS=(OWRONLY,OCREAT,OTRUNC),
// PATHMODE=(SIRUSR,SIWUSR,SIRGRP)
//STDERR DD PATH='/var/gpm/logs/gpm4cim&OS..trc',
// PATHOPTS=(OWRONLY,OCREAT,OTRUNC),
// PATHMODE=(SIRUSR,SIWUSR,SIRGRP)
//SYSPRINT DD SYSOUT=*
//SYSOUT DD SYSOUT=*
// PEND
```



```
MAXSESSIONS_HTTP(20) /* MaxNo of concurrent HTTP requests */
HTTP_PORT(8805) /* Port number for HTTP requests */
HTTP_ALLOW(*) /* Mask for hosts that are allowed */
HTTP_NOAUTH(*) /* No server can access without auth. */
INTERVAL(300) /* Length of the monitoring interval */
WIN_COMPLEX(WIN7PLEX) /* Name of system complex */
WIN_IMAGE(w7rmf1.boeb1ngen.de.ibm.com:5988) /* Hostname of member */
WIN_IMAGE(w7rmf2.boeb1ngen.de.ibm.com:5988)
```


- The GPM4CIM parameters are supplied with the platform specific configuration files /etc/gpm/gpm4[A|X|Z|W].cfg.
- This allows to run one separate GPM4CIM instance per platform.
- As a matter of course, multiple instances of GPM4CIM can be started for the same platform as well. In this case a dedicated copy of the configuration file should be provided per instance.
- The following configuration parameters are specifically for GPM4CIM:
 - AIX_COMPLEX | LNX_COMPLEX | LNZ_COMPLEX | WIN_COMPLEX:
 - Specifies an arbitrary name for the system complex.
 - AIX_IMAGE | LNX_IMAGE | LNZ_IMAGE | WIN_IMAGE:
 - Hostname or IP-address of one or more images running the specified operating system.
- Due to different resource models all images within the same complex must run the same operating system.

RMF XP Windows Support – Resource Model



- If we could follow the pure nature of CIM, resources and metrics are common in a computing environment, regardless of the operating system.
- However, the reality looks a bit different. We have to deal with lots of platform specific extensions of the resource model.
- That's why we decided to supply one GPM4CIM instance per operating system type.
- The RMF XP support for the Windows operating system adds another resource model with the WINDOWS_SYSTEM_COMPLEX as top level resource of the resource tree.

RMF XP Windows Support – Data Portal (Resource Tree)



The screenshots illustrate the RMF Performance Data Portal interface. The top-left screenshot shows the initial connection to the system complex. The top-right screenshot shows the children of the system complex. The bottom-left screenshot shows the children of a specific disk resource. The bottom-right screenshot shows the children of a specific image resource.

RMF Performance Data Portal

Welcome, you are connected to: ,WINPLEX,WINDOWS_S

Icon	Resource	Metrics	Attributes	Res-Type
	,WINPLEX,WINDOWS_SYSTEM_COMPLEX	Metrics	N/A	WINDOWS_IMAGE

RMF-DDS-Server GPM4CIM - F Validity Level: 3100

RMF Performance Data Portal

Children of: ,WINPLEX,WINDOWS_SYSTEM_COMPLEX

Icon	Resource	Metrics	Attributes	Res-Type
	,BR3MFNPM,WINDOWS_IMAGE	Metrics	N/A	WINDOWS_IMAGE
	IBM-GOEBU66ACKI,WINDOWS_IMAGE	Metrics	N/A	WINDOWS_IMAGE
	IBM-UO011B3251E,WINDOWS_IMAGE	Metrics	N/A	WINDOWS_IMAGE
	Imcc-12,WINDOWS_IMAGE	Metrics	N/A	WINDOWS_IMAGE

RMF Performance Data Portal

Children of: IBM-UO01LB3251E,*ALL_DISKS

Icon	Resource	Metrics	Attributes	Res-Type
	IBM-UO01LB3251E,C:DISK	Metrics	N/A	ALL_DISKS
	IBM-UO01LB3251E,D:DISK	Metrics	N/A	ALL_DISKS
	IBM-UO01LB3251E_TotalDISK	Metrics	N/A	ALL_DISKS


RMF Performance Data Portal

Children of: ,IBM-UO01LB3251E,WINDOWS_IMAGE

Icon	Resource	Metrics	Attributes	Res-Type
	IBM-UO01LB3251E,*ALL_NETWORK_PORTS	Metrics	N/A	ALL_NETWORK_PORTS
	IBM-UO01LB3251E,*LOCAL_FILE_SYSTEMS	Metrics	N/A	ALL_LOCAL_FILE_SYSTEMS
	IBM-UO01LB3251E,*LOGICAL_PROCESSOR	Metrics	N/A	LOGICAL_PROCESSOR

- Once you connect with a web browser to GPM4CIM, the System Complex appears as top level resource.
- Now you can navigate through the resource tree by simply clicking on every individual resource which is marked as hyperlink.

RMF XP Windows Support – Data Portal (Metrics)



RMF Performance Data Portal

Welcome, you are connected to: ,WINPLEX,WINDOWS_SY

Icon	Resource	Metrics	Attributes
	,WINPLEX,WINDOWS_SYSTEM_COMPLEX	Metrics	N/A

RMF-DDS-Server GPM4CIM - Functionality Level: 3100

RMF Performance Data Portal

Available metrics for: ,WINPLEX,WINDOWS_SYSTEM_COMPLEX

Metric description	Help	Id
by disk		
ReadOperations by disk	Explanation	444010
ReadThroughput by disk	Explanation	444020
WriteOperations by disk	Explanation	444030
WriteThroughput by disk	Explanation	444040
by local file system		
AvailableSpace by local file system	Explanation	440010
Capacity by local file system	Explanation	440020
by Windows image		
AvailableMemory by Windows image	Explanation	442010
AvailableProcessor by Windows image	Explanation	443010
CPUUsage by Windows image	Explanation	442020
Memory by Windows image	Explanation	442030
Processor by Windows image	Explanation	443020
by network port		
BytesReceived by network port	Explanation	441010
BytesTransmitted by network port	Explanation	441020
ErrorRate by network port	Explanation	441030
PacketsReceived by network port	Explanation	441040
PacketsTransmitted by network port	Explanation	441050

RMF Performance Data Portal


,WINPLEX,WINDOWS_SYSTEM_COMPLEX -- AvailableSpace by local file system [440010] (kilobytes)

Time Range: 10/23/2012 15:22:00 - 10/23/2012 15:23:00

Resource	Value
BRSMFNP.M.C:\	3.777893e+08
IBM-U001LB3251E.C:\	1.867911e+08
IBM-U001LB3251E.D:\	1.571719e+08
IBM-GOEBU66ACKI.D:\	1.554181e+08
IBM-GOEBU66ACKI.E:\	1.034539e+08
IBM-GOEBU66ACKI.C:\	9.109617e+07
tmcc-123-88.C:\	4156788


- When you click on the metrics column for a resource, the list of metrics that are applicable for this resource is displayed.
- Once you select the a certain metric from this list, the metric value(s) for the current interval are displayed instantly.

RMF XP Windows Support – Data Portal (Metric Values)



- Basically we distinguish two types of metrics:
 - Single valued metrics, which consist of just one value in terms of a string
 - List valued metrics, which consist of a list of name/value pairs
- As a matter of course, a certain value should be identical for the same resource, regardless whether it is represented as single value or as part of a list

RMF XP Windows Support – Data Portal (Metric Scope)



- All metrics are promoted to the System Complex as top-level resource.
- Once a metric is selected from this context, all resource names are prefixed with the system name in order to ensure that a certain resource can be identified uniquely within the System Complex.

RMF XP – SMF Recording Facility




Rationale

- ▶ Data source for after the facts analysis and accounting
- ▶ SMF records are the reliable standard on z/OS for decades
- ▶ One consistent repository for z/OS and distributed platforms
- ▶ Manage z/OS AND distributed platforms from z/OS
- ▶ Well-proven SMF postprocessing tools are already in place
- ▶ RMF infrastructure can be reused in terms of the RMF Sysplex Dataserver



- RMF Cross Platform Monitoring (RMF XP), introduced with z/OS V1R13 RMF, provides an integrated performance monitoring solution for heterogeneous operating systems running on IBM system z or zBX hardware
- The GPM4CIM server collects the data from the remote AIX, Linux and Windows systems by means of the standard CIM client API.
- However, beyond of the online monitoring capabilities for the new platforms, there was no possibility to store the data persistently for later reporting.
- Especially for z/OS customers, SMF records are the standard repository for all kinds of long term measurement and event data.
- With z/OS V2R1 the RMF GPM4CIM component is extended with the new SMF persistence capability as an additional vehicle for long-term performance analysis and capacity planning.


RMF XP & SMF Records



- Performance data collected from the distributed operating systems can be written to the new SMF Record Type 104 (x'68').
- The new SMF Record Type 104 is written to the currently active SMF Dataset of the z/OS system running the GPM4CIM started task.
- Alternatively a copy of the SMF record image can be written to the SMF Buffer of the RMF Sysplex Data Server. This alternative is not an RMF XP capability, it just exploits existing RMF infrastructure.

RMF XP & SMF Records...

One Subtype
per Metric Category




54 Complete your session evaluations online at www.SHARE.org/Pittsburgh-Eval

- The type 104 SMF record – RMF Distributed Platform Performance Data – serves as a container for all measurement data of non z/OS platforms.
- For each platform, the system writes the following range of subtypes:
 - Subtype 1-12 AIX on System p performance data
 - Subtype 20-31 Linux on System x performance data
 - Subtype 40-53: Linux on System z performance data
 - Subtype 60-64: Windows on System x performance data

RMF XP & SMF Records...

One Subtype
per Metric Category



- WINDOWS_SYSTEM_COMPLEX
 - WINDOWS_IMAGE
 - LOGICAL_PROCESSOR
 - ALL_LOCAL_FILE_SYSTEMS
 - LOCAL_FILE_SYSTEM
 - ALL_DISKS
 - DISK
 - ALL_NETWORK_PORTS
 - NETWORK_PORT

Subtypes 60-64

RMF XP & SMF Records...

One Subtype
per Metric
Category

AIX on System p	ST	Linux on System x	ST	Linux on System z	ST
AIX_ActiveMemoryExpansion	1	Linux_IPProtocolEndpoint	20	Linux_IPProtocolEndpoint	40
AIX_Processor	2	Linux_LocalFileSystem	21	Linux_LocalFileSystem	41
AIX_ComputerSystem	3	Linux_NetworkPort	22	Linux_NetworkPort	42
AIX_Disk	4	Linux_OperatingSystem	23	Linux_OperatingSystem	43
AIX_NetworkPort	5	Linux_Processor	24	Linux_Processor	44
AIX_FileSystem	6	Linux_UnixProcess	25	Linux_UnixProcess	45
AIX_Memory	7	Linux_Storage	26	Linux_Storage	46
AIX_OperatingSystem	8	Linux_KVM	30	Linux_zCEC	50
AIX_Process	9	Linux_Xen	31	Linux_zLPAR	51
AIX_SharedEthernetAdapter	10			Linux_zChannel	52
AIX_ActiveMemorySharing	11			Linux_zECKD	53
AIX_VirtualTargetDevice	12				

- One specific subtype is used to collect one individual CIM metric category according to the CIM data model on the affected platform.
- The CIM metric category, in return, is mapped to the resource models used by RMF XP on the supported platforms. For example, metrics from the CIM metric category AIX_ActiveMemoryExpansion are related to metrics from the ACTIVE_MEMORY_EXPANSION resource used by RMF XP for AIX on System p.
- You will find a complete mapping of CIM Metric Categories to RMF XP Resource Types in the description of the SMF 104 record in the ,z/OS V2R1.0 MVS System Management Facilities (SMF)' book.

RMF XP & SMF Records...

Windows on System x	ST
Windows_LocalFileSystem	60
Windows_NetworkPort	61
Windows_OperatingSystem	62
Windows_Processor	63
Windows_Storage	64

One Subtype
per Metric
Category

RMF XP & SMF Records...

Offsets	Name	Length	Format	Description
Common header for SMF record type 104				
0	0 SMF104LEN	2	binary	Record length. This field and the next field (total of four bytes) form the RDW (record descriptor word).
2	2 SMF104SEG	2	binary	Segment descriptor (see record length field).
4	4 SMF104FLG	1	binary	System indicator: <div> <div>Bit</div> <div>Meaning When Set</div> </div> <div> <div>0</div> <div>New record format</div> </div> <div> <div>1</div> <div>Subtypes used</div> </div> <div> <div>2</div> <div>Reserved</div> </div> <div> <div>3-6</div> <div>Version indicators*</div> </div> <div> <div>7</div> <div>System is running in PR/SM mode</div> </div>
5	5 SMF104RTY	1	binary	Record type 104 (X'68').
6	6 SMF104TME	4	binary	Time since midnight, in hundredths of a second, that the record was moved into the SMF buffer.
10	A SMF104DTE	4	packed	Date when the record was moved into the SMF buffer, in the form 0cyyddF.
14	E SMF104SID	4	EBCDIC	System identification (from the SMFPRMxx SID parameter).
18	12 SMF104SSI	4	EBCDIC	Subsystem identification (GPM).
22	16 SMF104STY	2	binary	Record subtype.
24	18 SMF104TRN	2	binary	Number of triplets in this record. A triplet is a set of three SMF fields (offset/length/number values) that defines a section of the record. The offset is the offset from the RDW.
26	1A	2		Reserved.
28	1C SMF104PRS	4	binary	Offset to RMF XP product section from the RDW.
32	20 SMF104PRL	2	binary	Length of RMF XP product section.
34	22 SMF104PRN	2	binary	Number of RMF XP product sections.
Header extension for all subtypes				
36	24 SMF104ICS	4	binary	Offset to image control section from the RDW.
40	28 SMF104ICL	2	binary	Length of image control section.
42	2A SMF104ICN	2	binary	Number of image control sections.
44	2C SMF104MES	4	binary	Offset to metric section from the RDW.
48	30 SMF104MEL	2	binary	Length of metric section.
50	32 SMF104MEN	2	binary	Total number of metric sections.

SMF Header
with common
Layout

58 Complete your session evaluations online at www.SHARE.org/Pittsburgh-Eval

- GPM4CIM writes one SMF record subtype per interval. That means that one subtype contains the performance data for all systems where GPM4CIM is connected to.
- Control sections will be provided to allow exploiters of the SMF records to assign the performance data to the appropriate systems.
- The structure of the SMF record type 104 follows the general guidelines for SMF records including the common header.
- All sections can be addressed by means of so called triplets, where a triplet describes individual sections with offset, length and number.
- This allows to extract data from the new SMF record with standard SMF postprocessing tools.

RMF XP & SMF Records...

RMF
Product Section
with common Layout

Offsets	Name	Length	Format	Description
0	0 SMF104MFV	2	packed	RMF version number.
2	2 SMF104PRD	8	EBCDIC	Product name (<i>RMF XP</i>).
10	A SMF104IST	4	packed	Time that the RMF XP measurement interval started, in the form <i>0hhmmssF</i> , where <i>hh</i> is the hours, <i>mm</i> is the minutes, <i>ss</i> is the seconds, and <i>F</i> is the sign.
14	E SMF104DAT	4	packed	Date when the RMF measurement interval started, in the form <i>0cyydddF</i> .
18	12 SMF104INT	4	packed	Duration of RMF measurement interval, in the form <i>mmsstttF</i> , where <i>mm</i> is the minutes, <i>ss</i> is the seconds, <i>ttt</i> is the milliseconds, and <i>F</i> is the sign. The end of the measurement interval is the sum of the recorded start time and this field.
22	16 SMF104LGO	8	binary	Offset GMT to local time (STCK format).
30	1E	2		Reserved.
32	20 SMF104XPL	2	binary	RMF XP functionality level.
34	12 SMF104CPX	24	EBCDIC	System complex name, specified with the COMPLEX parameter in the <i>cfg4AI/XIZ</i> configuration file.
58	3A SMF104OSL	8	EBCDIC	Operating system label served by RMF XP (AIX or LINUX).
66	42 SMF104PLT	2	binary	Platform type served by RMF XP: 0 System p 1 System x 2 System z
68	44 SMF104MVS	8	EBCDIC	z/OS software level for the current system (consists of an acronym and the version, release, and modification level - <i>ZVvrrmm</i>).
76	4C SMF104XNM	8	EBCDIC	Sysplex name of the current sysplex as defined in parmlib member COUPLExx.
84	54 SMF104SNM	8	EBCDIC	System name for the current system as defined in parmlib member IEASYSxx SYSNAME parameter.

- The SMF 104 RMF Product Section is slightly different from the SMF 70-79 records since a subset of information is not available for the new platforms (e.g. cycle length, sample number).
- On the other hand, the SMF 104 RMF Product Section contains information which is not available in a z/OS environment (e.g. SMF104CPX, SMF104OSL, SMF104PLT).

RMF XP & SMF Records...

Offsets	Name	Length	Format	Description
0	0 SMF104MIM	64	EBCDIC	Name of this monitored image, extracted from the CIM metrics collection.
64	40 SMF104TIM	14	EBCDIC	Timestamp in the format <i>yyyymmddhhmmss</i> , extracted from the CIM metrics collection.
78	4E SMF104DUR	14	EBCDIC	Interval duration in the format <i>yyyymmddhhmmss</i> , extracted from the CIM metrics collection.
92	5C SMF104CIM	64	EBCDIC	Name of the image where the CIM server is running, specified with the IMAGE parameter in the <i>cfg4AIXIZ</i> configuration file.
156	9C SMF104OST	4	EBCDIC	Operating system type where the CIM server is running, extracted from the OSType attribute of the CIM_Operating_System instance: 9 AIX 36 Linux
160	A0 SMF104OSV	64	EBCDIC	Operating system version where the CIM server is running, extracted from the version attribute of the CIM_Operating_System instance.
224	E0 SMF104CTZ	4	EBCDIC	Current time zone, extracted from the CurrentTimeZone attribute of the CIM_Operating_System instance. This value represents the GMT offset in minutes.
228	E4 SMF104MIND	2	binary	Index of first metric section associated with this monitored image.
230	E6 SMF104MNUM	2	binary	Number of metric sections associated with this monitored image.


Image Control Section

Offsets	Name	Length	Format	Description
0	0 R10406MNAME	64	EBCDIC	Name of measured element, extracted from the MeasuredElementName attribute of the CIM_BaseMetricValue instance.
64	40 R10406AS	8	floating	Available space for this filesystem in megabytes. (AvailableSpace)
72	48 R10406TS	8	floating	Total space for this filesystem in megabytes. (TotalSpace)
80	50 R10406US	8	floating	Used space for this filesystem in megabytes. (UsedSpace)

Metric Section

- The SMF Type 104 Record contains performance data that has been collected from one or more systems resp. images.
- There is one image control section per image. Beyond general information (e.g. time stamps) the image control section describes the corresponding metric sections with the measured elements and their metric values.

RMF XP & SMF Records...



- All image control sections are located consecutively right behind the RMF product section.
- In the same way, all metric sections are following right behind the last image control section.
- The metric section index and number within the image control section allows to identify the metric sections belonging to a certain image.
- Since one SMF record is limited to the length of 32756 bytes, an individual record can be splitted and not all metric sections for a certain image might be located in the same record.
- However, in any case, one single record is self-containing: that means, a meaningful report can be produced just by using one single record. There is no need to combine multiple records from the same subtype for reporting purposes.

RMF XP & SMF Records...

RMF ERBSCAN
Utility maps all
Sections of the SMF
Type 104 record

-> AIX Image Control Section (2)

```
#1:  +0000:  97F69994 86F10000 00000000 00000000 *p6rmf1      *
      +0010:  00000000 00000000 00000000 00000000 *              *
      +0020:  00000000 00000000 00000000 00000000 *              *
      +0030:  00000000 00000000 00000000 00000000 *              *
      +0040:  F2F0F1F1 F0F9F0F8 F1F6F2F7 F0F3F0F0 *2011090816270300*
      +0050:  F0F0F0F0 F0F0F0F0 F0F1F0F1 97F69994 *000000000101p6rm*
      +0060:  86F14882 96858293 89958785 95488485 *f1.boeblingen.de*
      +0070:  48898294 48839694 00000000 00000000 *.ibm.com      *
      +0080:  00000000 00000000 00000000 00000000 *              *
      +0090:  00000000 00000000 00000000 F9000000 *              9 *
      +00A0:  F64BF14B F04BF000 00000000 00000000 *6.1.0.0      *
      +00B0:  00000000 00000000 00000000 00000000 *              *
      +00C0:  00000000 00000000 00000000 00000000 *              *
      +00D0:  00000000 00000000 00000000 00000000 *              *
      +00E0:  F6F00000 00000002 00000000 00000000 *60           *
```

```
-> Image name      : p6rmf1
-> Operating system : 6.1.0.0
-> First metric sec. : #1
-> Number of metrics : 2
```

-> AIX_ProcessorMetrics (4)

```
#1:  +0000:  8397A4F0 00000000 00000000 00000000 *cpu0        *
      +0010:  00000000 00000000 00000000 00000000 *              *
      +0020:  00000000 00000000 00000000 00000000 *              *
      +0030:  00000000 00000000 00000000 00000000 *              *
      +0040:  414C5441 355475A3 425F383E 425AEE63 * <è èîîâ^ â!ôÁ*
      +0050:  412E1298 88F861A6 411E41B3 28B6D86F * qh8/w  · 1Q?*
      +0060:  3F28064E A3A70EA2 00000000 00000000 * +tx s      *
```

```
-> Measured element : cpu0
-> List of values   :
                        '414C5441355475A3'X  4.77057000
                        '425F383E425AEE63'X  95.2196999
                        '412E129888F861A6'X  2.87954000
                        '411E41B328B6D86F'X  1.89104000
                        '3F28064EA3A70EA2'X  0.00977164000
```

- The RMF utility ERBSCAN has been extended to support the new SMF type 104
- Beyond the header sections, the content of the image sections as well as the metric sections is displayed in hex and in character format.
- The individual metric values are stored in double floating point format. ERBSCAN translates all the values to the decimal format and displays it right behind the hexdump section.

RMF XP & SMF Records...

```
//GPM4CIM PROC OS=A
//STEP1 EXEC PGM=BPXBATCH,TIME=NOLIMIT,REGION=0M,
// PARM='PGM /usr/lpp/gpm/bin/gpm4cim cfg=/etc/gpm/gpm4cim.cfg'
//STDENV DD PATH='/etc/gpm/gpm4cim.env'
//STDOUT DD PATH='/var/gpm/logs/gpm4cim&OS..out',
// PATHOPTS=(OWRONLY,OCREAT,OTRUNC),
// PATHMODE=(SIRUSR,SIWUSR,SIRGRP)
//STDERR DD PATH='/var/gpm/logs/gpm4cim&OS..trc',
// PATHOPTS=(OWRONLY,OCREAT,OTRUNC),
// PATHMODE=(SIRUSR,SIWUSR,SIRGRP)
//SYSPRINT DD SYSOUT=*
//SYSOUT DD SYSOUT=*
// PEND
```



```
MAXSESSIONS_HTTP(20) /* MaxNo of concurrent
HTTP_PORT(8805) /* Port number for HT
HTTP_ALLOW(*) /* Mask for hosts tha
HTTP_NOAUTH(*) /* No server can acces
INTERVAL(300) /* Length of the monitor
AIX_COMPLEX(WEBPLEX) /* Name of system complex
AIX_IMAGE(p6rmf1.boeblingen.de.ibm.com:5988) /* Hostname of member
AIX_IMAGE(p6rmf2.boeblingen.de.ibm.com:5988) /*
RECORD /* Write SMF Records
```

New global Option:
RECORD / NORECORD
Default: NORECORD



Change RECORD Option dynamically: F GPM4CIM, RECORD/NORECORD
✓ GPM253I SMF RECORDING IS NOW ON/OFF


- A new option RECORD/NORECORD within the RMF XP configuration file (/etc/gpm/gpm4[A|X|Z|W].cfg) is introduced to specify that the GPM4CIM server writes SMF type 104 records
- The scope of this option is global, this means that the option is applied to all supported subtypes.
- Of course, SMF recording can also be enabled or disabled with a MODIFY command:

F GPM4CIM,[NO]RECORD.

- Once the RECORD parameter is set to on, SMF 104 records are written frequently and the completion of an interval is indicated by new message:

GPM280I RMF XP INTERVAL PROCESSING FOR name COMPLETE

RMF XP & SMF Records...



- Use the SMF built-in facilities in order to control the SMF 104 recording on subtype level. You can dynamically switch on or off SMF recording for a specific subtype by changing the active SMFPRMxx parmlib member. For example:

```
SYS(TYPE(30,42,70:79,103,104(1:12,20:31,40:53,60:64),108),...
```

- The capability to receive and hold real-time copies of SMF records in the in-storage SMF buffer of the RMF Sysplex Data Server is a standard feature of RMF. To use this feature, modify the PARM statement of the RMF procedure to include SMF type 104.

z/OSMF Application Linking (Resource Monitoring & WLM)



- ▶ The definitions of Workload Management determine the performance behavior of the systems.
- ▶ Resource Monitoring visualizes the performance behavior.
- ▶ Link z/OSMF WLM and RM to each other:
 - ⇒ When you work with WLM service definitions:
Jump to Resource Monitoring to visualize the resulting performance.
 - ⇒ When you detect abnormal metric values in Resource Monitoring:
Jump to Workload Management to look at the service definition.
- ▶ Performance metrics can be viewed more easily in context with the active service definition/policy and vice versa.



65 Complete your session evaluations online at www.SHARE.org/Pittsburgh-Eval

- The new z/OSMF Application Linking allows to link the following tasks of the Performance category to each other in context:
 - The z/OSMF Workload Management task, which allows you to define, manage, install and activate your WLM service definitions and policies.
 - The z/OSMF System Status, which provides a quick performance status overview of all the sysplexes in your data center.
 - The z/OSMF Resource Monitoring task, which allows you to define monitoring dashboards that show performance results in detailed bar charts.
- z/OSMF Application Linking support is available for z/OS 1.13 with the following new function APARs:
 - PM74502 (z/OSMF Base)
 - PM74508 (Resource Monitoring)
 - PM74517 (WLM)
 - PM74925 (WLM)
- The following foils show examples of links between the z/OSMF WLM and Resource Monitoring plug-ins.

From WLM Status to RM System Status

Welcome x Workload Man... x

Workload Management [Help](#)

Overview WLM Status x

WLM Status for Sysplex ZMF1PLEX from System ZMF2

Active Service Policy ([View performance of active policy](#))

Name: STANDARD
Description: BB default policy 1
Activated: Jan 29, 2013 3:14:59 PM GMT
Activated by: jbau from system ZMF2
Related service definition: DEFAULT
Functionality level: 4
Installed: Jan 29, 2013 3:14:59 PM GMT
Installed by: jbau from system ZMF2

Systems ([View performance of systems](#))

Actions Search

Name	Used Service Policy	Activated (GMT)	WLM Status	GPMP Status	WLM Version Level	CD Le
Filter	Filter	Filter	Filter	Filter	Filter	Filter
ZMF1	STANDARD	Jan 29, 2013 3:14:59 PM	Active	Unavailable		
ZMF2	STANDARD	Jan 29, 2013 3:14:59 PM	Active	Unavailable	25	3
ZMF3	STANDARD	Jan 29, 2013 3:14:59 PM	Active	Unavailable		
ZMF4	STANDARD	Jan 29, 2013 3:14:59 PM	Active	Unavailable		
ZMF5	STANDARD	Jan 29, 2013 3:14:59 PM	Active	Unavailable		

Total: 5

Installed Service Definition

Name: DEFAULT
Description: BB default WLM policy - test
Installed: Jan 29, 2013 3:14:59 PM GMT
Installed by: jbau from system ZMF2

[Refresh](#) ☐ Automatic refresh Last refresh: Jan 30, 2013 11:13:10 AM local time (Jan 30, 2013 10:13:10 AM GMT)

66 Complete your session evaluations online at www.SHARE.org/Pittsburgh-Eval

- By linking the Workload Management task and the System Status task of the z/OSMF Resource Monitoring plug-in, you can open the System Status task from the Workload Management task and view the status of the sysplex.
- From System Status task you can open the Workload Management task and view the active service definition, active service policy or WLM status.

RM System Status




Welcome x Workload Man... x System Status x [Help](#)

System Status

Use this page to quickly assess the performance of the workloads running on the sysplexes in your installation. You can also use this page to define the target systems for the sysplexes and AIX or Linux system complexes that you want to monitor in the Resource Monitoring task.

Resources

☒ ☐ Actions ▼

Resource Filter	System Type Filter	Connectivity Filter	Performance Index Status Filter	Related Service Definition Filter	Active WLM Policy Filter
<input checked="" type="checkbox"/> LOCALPLEX	z/OS	Connected	 PI > 1 for unimportant periods	DEFAULT	STANDARD
<input type="checkbox"/> SCLMPLEX	z/OS	Connected	 PI <= 1 for all periods	Default	STANDARD
<input type="checkbox"/> SYSPLEX	z/OS	Connected	 PI <= 1 for all periods	SYSTES2	STANDARD
<input type="checkbox"/> IRDPLEX	z/OS	Error			

Total: 4, Selected: 1

Last refresh: Jan 30, 2013 11:18:00 AM local time (Jan 30, 2013 10:18:00 AM GMT)

☒ Automatic refresh

From RM System Status

Welcome x
Workload Man... x
System Status x

Help

System Status

Use this page to quickly assess the performance of the workloads running on the sysplexes in your installation. You can also use this page to define the target systems for the sysplexes and AIX or Linux system complexes that you want to monitor in the Resource Monitoring task.

Resources

Resource Filter	System Type Filter	Connectivity Filter	Performance Index Status Filter	Related Service Definition Filter	Active WLM Policy Filter
<input checked="" type="checkbox"/> LOCALPLEX	z/OS	Connected	<div> <div>⚠️</div> <div>PI > 1 for unimportant periods</div> </div>	DEFAULT	STANDARD
<input type="checkbox"/> SCLMPLEX		Connected	<div> <div>✅</div> <div>PI <= 1 for all periods</div> </div>	Default	STANDARD
<input type="checkbox"/> SYSPLEX			<div> <div>✅</div> <div>PI <= 1 for all periods</div> </div>	SYSTES2	STANDARD
<input type="checkbox"/> RDPLEX	z/OS				

⌵

Actions

Modify Entry

Remove Entry

View

Performance Index Details

Active WLM Service Definition

Active WLM Policy

WLM Status

Total: 4, Selected: 1

Refresh

Last refresh: Jan 30, 2013 11:20:04 AM local time (Jan 30, 2013 10:20:04 AM GMT)

☒ Automatic refresh

From RM System Status

Welcome
Workload Man...
System Status
Help

System Status

Use this page to quickly assess the performance of the workloads running on the sysplexes in your installation. You can also use this page to define the target systems for the sysplexes and AIX or Linux system complexes that you want to monitor in the Resource Monitoring task.

Resources

Resource	System Type	Connectivity	Performance Index Status	Related Service Definition	Active WLM Policy
LOCALPLEX	z/OS	Connected	PI > 1 for unimportant periods	DEFAULT	STANDARD
SCLMPLEX		Connected	PI <= 1 for all periods	Default	STANDARD
SYSPLEX			PI <= 1 for all periods	SYSTES2	STANDARD
RDPLEX	z/OS				

Modify Entry
Remove Entry
View
Performance Index Details
Active WLM Service Definition
Active WLM Policy
WLM Status

Resource Monitoring

Dashboards
Performance Index - LOCALPLEX

Performance Index - LOCALPLEX (Running)

Start
Pause
Save
Actions

Important Service Class Periods

Service Class Periods

PRDTSO.1 | 0

STCCMD.1 | 0.67

PRDTSO.1 | 0

Total: 4, Selected: 1

Refresh
Last refresh: Jan 30, 2013 11:20:04 AM local time (Jan 30, 2013 10:20:04 AM GMT)

Automatic refresh

From RM System Status

Welcome x
Workload Man... x
System Status x
Help

System Status

Use this page to quickly assess the performance of the workloads running on the sysplexes in your installation. You can also use this page to define the target systems for the sysplexes and AIX or Linux system complexes that you want to monitor in the Resource Monitoring task.

Resources

Resource	System Type	Connectivity	Performance Index Status	Related Service Definition	Active WLM Policy
<input checked="" type="checkbox"/> LOCALPLEX	z/OS	Connected	PI > 1 for unimportant periods	DEFAULT	STANDARD
<input type="checkbox"/> SCLMPLEX		Connected	PI <= 1 for all periods	Default	STANDARD
<input type="checkbox"/> SYSPLEX			PI <= 1 for all periods	SYSTEMS2	STANDARD
<input type="checkbox"/> RDPLEX	z/OS				

Modify Entry
Remove Entry
View
Performance Index Details
Active WLM Service Definition
Active WLM Policy
WLM Status

Resource Monitoring

Workload Management

Overview x
WLM Status x
View DEFAULT x

This service definition is installed and policy STANDARD is active

Service Definition Details

Service definition name:
DEFAULT

Description:
BB default WLM policy - test

Functionality level:
004

Total: 4, Selected: 1
Refresh Last refresh: Jan 30, 2013 11:20:04 AM local time (Jan 30, 2013 10:20:04 AM GMT)
☒ Automatic refresh

From RM System Status

Welcome x Workload Man... x System Status x [Help](#)

System Status

Use this page to quickly assess the performance of the workloads running on the sysplexes in your installation. You can also use this page to define the target systems for the sysplexes and AIX or Linux system complexes that you want to monitor in the Resource Monitoring task.

Resources

Resource	System Type	Connectivity	Performance Index Status	Related Service Definition	Active WLM Policy
<input checked="" type="checkbox"/> LOCALPLEX	z/OS	Connected	PI > 1 for unimportant periods	DEFAULT	STANDARD
<input type="checkbox"/> SCLMPLEX		Connected	PI <= 1 for all periods	Default	STANDARD
<input type="checkbox"/> SYSPLEX			PI <= 1 for all periods	SYSTES2	STANDARD
<input type="checkbox"/> RDPLEX	z/OS				

Actions:
☒ ☐
 Filter Filter Filter Filter Filter Filter

Context menu for LOCALPLEX:
 Modify Entry
 Remove Entry
 View
 Performance Index Details
 Active WLM Service Definition
 Active WLM Policy
 WLM Status

Resource Monitoring

Workload Management

Workload Management

Overview WLM Status x View DEFAULT x

Service Policies > Properties This service definition is installed and policy STANDARD is active

Properties for Active Service Policy

Service policy name: STANDARD Description: BB default policy 1

Service Class Overrides Resource Group Overrides

Table view: Tree

Service Class	Period	Importance	Duration	Goal Type	Response Goal
Filter	Filter	Filter	Filter	Filter	Filter

Total: 4, Selected: 1

Refresh Last refresh: Jan 30, 2013 11:20:04 AM local time (Jan 30, 2013 10:20:04 AM local time)

☒ Automatic refresh

From RM System Status

Welcome x Workload Man... x System Status x Help

System Status

Use this page to quickly assess the performance of the workloads running on the sysplexes in your installation. You can also use this page to define the target systems for the sysplexes and AIX or Linux system complexes that you want to monitor in the Resource Monitoring task.

Resources

Resource	System Type	Connectivity	Performance Index Status	Related Service Definition	Active WLM Policy
LOCALPLEX	z/OS	Connected	PI > 1 for unimportant periods	DEFAULT	STANDARD
SCLMPLEX		Connected	PI <= 1 for all periods	Default	STANDARD
SYSplex			PI <= 1 for all periods	SYSTES2	STANDARD
RDPLEX	z/OS				

Actions: Modify Entry, Remove Entry, View, Performance Index Details, Active WLM Service Definition, Active WLM Policy, WLM Status

Resource Monitoring

Workload Management

Overview WLM Status x View DEFAULT x

Workload Management

Overview WLM Status x

WLM Status for Sysplex ZMF1PLEX from System ZMF2

Active Service Policy (View performance of active policy)

Name: STANDARD
 Description: BB default policy 1
 Activated: Jan 29, 2013 3:14:59 PM GMT
 Activated by: jbau from system ZMF2
 Related service definition: DEFAULT
 Functionality level: 4
 Installed: Jan 29, 2013 3:14:59 PM GMT
 Installed by: jbau from system ZMF2

Standard is active

Refresh Last refresh: Jan 30, 2013 11:20:04 AM local time (Jan 30, 2013 10:20:04 AM)
 Automatic refresh

From WLM to RM Dashboard (Service Classes)



Welcome x Workload Man... x

Workload Management [Help](#)

Overview WLM Status x

WLM Status for Sysplex ZMF1PLEX from System ZMF2

Active Service Policy [\(View performance of active policy\)](#)

Name: STANDARD
Description: BB default policy 1
Activated: Jan 29, 2013 3:14:59 PM GMT
Activated by: jbau from system ZMF2
Related service definition: DEFAULT
Functionality level: 4
Installed: Jan 29, 2013 3:14:59 PM GMT
Installed by: jbau from system ZMF2

Systems [\(View performance of systems\)](#)

Actions						Search
Name	Used Service Policy	Activated (GMT)	WLM Status	GPMP Status	WLM Version Level	CD Level
Filter	Filter	Filter	Filter	Filter	Filter	Filter
ZMF1	STANDARD	Jan 29, 2013 3:14:59 PM	Active	Unavailable		
ZMF2	STANDARD	Jan 29, 2013 3:14:59 PM	Active	Unavailable	25	3
ZMF3	STANDARD	Jan 29, 2013 3:14:59 PM	Active	Unavailable		
ZMF4	STANDARD	Jan 29, 2013 3:14:59 PM	Active	Unavailable		
ZMF5	STANDARD	Jan 29, 2013 3:14:59 PM	Active	Unavailable		

Total: 5

Installed Service Definition

Name: DEFAULT
Description: BB default WLM policy - test
Installed: Jan 29, 2013 3:14:59 PM GMT
Installed by: jbau from system ZMF2


[Refresh](#) ☐ Automatic refresh Last refresh: Jan 30, 2013 11:13:10 AM local time (Jan 30, 2013 10:13:10 AM GMT)




73 Complete your session evaluations online at www.SHARE.org/Pittsburgh-Eval

- By linking the Workload Management task and the Resource Monitoring task, you can open dashboards with performance metrics for service classes, workloads and report classes from within the Workload Management task.
- From a Resource Monitoring dashboard with performance metrics for service classes, workloads and report classes you can open the corresponding information in the WLM service definition.

RM Dashboard – WLM Service Class Performance



From RM Dashboard to WLM Service Classes



WLM Service Classes

Welcome x Workload Man... x System Status x Resource Mon... x

Workload Management Help

Overview WLM Status x View DEFAULT x

This service definition is installed and policy STANDARD is active Notes Switch To

Service Classes

☒ Actions Table view: Tree Search

Name	Period	Importance	Duration	Goal Type	Response Time Goal (hh:mm:ss.ttt)	Percent Goal	Velocity Goal	CPU Critical	Resource Group	Workload
Filter	Filter	Filter	Filter	Filter	Filter	Filter	Filter	Filter	Filter	Filter
<input type="checkbox"/> BATCH1								No		BATCH1
<input type="checkbox"/> BATCH2								No		BATCH2
<input type="checkbox"/> BATCHHI								No		BATCHHI
<input type="checkbox"/> BATCHLOW								No		BATCHLOW
<input type="checkbox"/> BATCHMED								No		BATCHMED
<input type="checkbox"/> BATCHRSP								No		BATCHRSP
<input type="checkbox"/> DISCRET								No		DISCRET
<input checked="" type="checkbox"/> HOTTSO	1	1		Percentile Response Time	00:00:00.500	95		No	REGTSO	TSO
<input type="checkbox"/> IRLM								No		IRLM
<input type="checkbox"/> OE								No	REGTSO	OMVS
<input type="checkbox"/> OMVS								No		OMVS
<input type="checkbox"/> OMVSKERN								No		OMVSKERN
<input type="checkbox"/> PRDTSO								No	REGTSO	TSO
<input type="checkbox"/> STCCMD								No	REGSTC	STC
<input type="checkbox"/> STCLO								No	BATCHVEL	STC
<input type="checkbox"/> STCSYS								No	HIGHPRTY	STC
<input type="checkbox"/> STORPROC								No		BATCH
<input type="checkbox"/> TSDEVEN								No		BATCH

Total: 62, Selected: 1

From WLM to RM Dashboard (Workloads)

Welcome x Workload Man... x System Status x Resource Mon... x

Workload Management [Help](#)

Overview WLM Status x Modify DEFAULT x

This service definition is installed and policy STANDARD is active [Notes](#) [Switch To](#)

Workloads

☒ ☐ ☐ Actions

Name	Messages	Last Modified (GMT)	Modified By
Filter	Filter	Filter	Filter
<input type="checkbox"/> *APPC		Mar 30, 2011 2:31:17 PM	debug1
<input type="checkbox"/> *BATCH		Oct 16, 1998 11:58:16 AM	tag
<input type="checkbox"/> *CICS		Oct 16, 1998 11:58:30 AM	tag
<input type="checkbox"/> *OMVS		Oct 16, 1998 12:01:03 PM	tag
<input type="checkbox"/> *STC		Oct 16, 1998 12:01:45 PM	tag
<input checked="" type="checkbox"/> *TSO		Oct 16, 1998 12:01:52 PM	tag

Context menu options:


- Cut to Clipboard
- Copy to Clipboard
- Delete...
- View Cross References
- View Messages
- View Performance of Selected
- New...
- Paste
- View Performance of All
- Select All
- Deselect All
- Configure Columns...
- Modify Filters...
- Hide Filter Row
- Clear Filters
- Modify Sort...
- Clear Sorts
- Clear Search

Total: 6, Selected: 1


[Reapply Filter and Sort](#)

[OK](#) [Apply](#) [Reset](#) [Cancel](#)

RM Dashboard – WLM Workload Performance



Customization and Persistence



- ⇒ The user can customize dashboards opened by Application Linking and save them to the Dashboards list.
- ⇒ Then the Dashboard can be opened directly in Resource Monitoring using the Dashboards list.
- ⇒ Subsequent application linking events will use the saved dashboard.


Conditions for Application Linking between WLM & RM



- ▶ In the Workload Management task, the *View Performance...* actions and links are only available if the service definition in the *View/Modify* tab is currently activated in the Sysplex.
- ▶ In the System Status task, the WLM related *View* actions (and corresponding links) are only available if the selected resource is the z/OS sysplex where z/OSMF is running in (local sysplex).
- ▶ In a monitoring dashboard, the context menu icon is only visible if the performance data is retrieved from the local sysplex and the chart is related to WLM definitions, i.e.,
 - ⇒ The resources in the chart are WLM service classes, service class periods, report classes, or workloads.
 - ⇒ The metric is filtered by a workscope of a WLM service class, service class period, report class, or workload.
(Example: % using by MVS image [BATCH,S] , where [BATCH,S] means: filtered by workscope of service class BATCH)




Resource Monitoring – Windows Support



81 Complete your session evaluations online at www.SHARE.org/Pittsburgh-Eval


- The Resource Monitoring plugin for z/OSMF V2.1 can exploit the new Windows performance data provided by RMF XP on a z/OS 2.1 system.
- Just define the connection to GPM4CIM with the System Status task.
- The z/OSMF Resource Monitoring will instantly start to retrieve the performance data and displays the connection status in the System Status window.
- You can now use all the Windows performance metrics provided by GPM4CIM when you create a new Monitoring Dashboard.

Resource Monitoring – Windows Support...



The screenshot shows the IBM z/OS Management Facility (zOSMF) web interface in a Firefox browser. The address bar shows the URL <https://boezmf4.boeblingen.de.ibm.com:9443/zosmf/>. The page title is "IBM z/OS Management Facility" and the user is logged in as "Welcome bhbe". The left navigation pane includes sections like Welcome, Notifications, Workflows, Links, Performance, Problem Determination, Software, z/OS Classic Interfaces, z/OSMF Administration, and z/OSMF Settings. The main content area is titled "Resource Monitoring" and shows a dashboard for "\$WINPLEX Health Check". Under the "Add Metric" section, the "Add to metric group" is set to "Network Overview", the "Selected resource" is "xbxrmf4,*_ALL_NETWORK_PORTS", and the "Selected metric" is "BytesTransmitted by network port". Below this, there is a "Quick filter" input field and a list of "Available metrics" including "BytesReceived by network port", "BytesTransmitted by network port", "ErrorRate by network port", "PacketsReceived by network port", and "PacketsTransmitted by network port".

Resource Monitoring – Windows Support...



Resource Monitoring – Historical Reporting

Welcome x Resource Mon... x

Resource Monitoring

Dashboards Storage Soaker x

Storage Soaker (Running)

Start Pause Stop Save Actions

▼ Active & Fixed Frames (WLM View)

Metric Group	Value
SYSTEM.1	2907
SYSSTC.1	4436
STCDEF.1	3530
GPMSERVE.1	261
OE.2	0
OMVSKERN.1	0

05/02/2014 10:35:00 - 05/02/2014 10:36:00 (1/1)

Retrieve Historical Data

To retrieve historical data from the DDS, specify the metric groups, timeframe, and range. This action may generate significant amount of overhead on the DDS host, especially for long time ranges.

Metric groups:

- Active & Fixed Frames (WLM View)
- Active Frames
- Fixed Frames

Timeframe:

Condition: Past Amount: 2 Unit: Hours

Data sample range:

☐ Use the default range

☒ Specify the range in seconds: 600

OK Restore Defaults Cancel Help

Retrieve performance data from the past accordingly to the content of the RMFGAT in-storage buffer or the RMFGAT VSAM Data Sets

Resource Monitoring – Spreadsheet Export

Export Dashboard

Step1: Select Scope and Intervals
✓ Step2: Select Metrics and Resources

Select the scope of data to export

Scope of Data to Export

☒ Metric group:
Active & Fixed Frames

☐ Include all metrics

☐ Include a selection

☐ Entire dashboard with all metrics

Range of Intervals to Export

Start time of first interval
03/03/2014 14:25:00

End time of last interval
03/03/2014 14:45:00

Select the metrics and resources to include when exporting the metric group.

Metric group to export: Active & Fixed Frames (WLM View)

Metrics:

S1.*.STORAGE # frames fixed by WLM service class period
S1.*.STORAGE # frames active by WLM service class period

Resources:

OMVS.1
OMVS.3
SHRDB2.1
STCHI.1
STCLO.1
STCMD.1
SYSOTHER.1
SYSSTC.1
SYSTEM.1

< Back Next > Finish Cancel




Storage Soaker_Active & Fixed Frames (WLM View).csv
Storage Soaker_Active Frames.csv
Storage Soaker_Fixed Frames.csv

Information and Tools

► RMF website: www.ibm.com/systems/z/os/zos/features/rmf/


- ⇒ Product information, newsletters, presentations, ...
- ⇒ Downloads
 - Spreadsheet Reporter
 - RMF PM Java Edition
 - Postprocessor XML Toolkit

► RMF email address: rmf@de.ibm.com



Users Guide:
New RMF
XP Chapter

► Documentation and news:

- 
- ⇒ RMF Performance Management Guide, SC33-7992
 - ⇒ RMF Report Analysis, SC33-7991
 - ⇒ RMF User's Guide, SC33-7990
 - ⇒ Latest version of PDF files can be downloaded from:
www.ibm.com/systems/z/os/zos/bkserv/v2r1pdf/#rmf

Function Reference

Function	Availability
Flash Memory & Pageable Large Pages Support of Coupling Facility Flash Memory zEnterprise Data Compression Express Shared Memory Communication Reporting I/O Interrupt Delay Time IFB Link Reporting Crypto CEX4 Statistics Warning Track Support	APAR OA38660 APAR OA40515 z/OS 2.1 RMF z/OS 2.1 RMF APAR OA39993 APAR OA37826 APAR OA37016 APAR OA37803
Postprocessor XML Formatted Reports	z/OS 1.11 RMF – z/OS 2.1 RMF
z/OSMF Resource Monitoring – Windows Support z/OSMF Resource Monitoring – Application Linking z/OSMF Resource Monitoring – Historical Reporting z/OSMF Resource Monitoring – Spreadsheet Export	z/OS 2.1 z/OS 2.1 APAR PI08825 APAR PI08825
RMF XP – Windows Support RMF XP – SMF 104 Recording Facility	z/OS 2.1 RMF z/OS 2.1 RMF

zEC12
Enhancements